

You can search for the updated part code through ITSELF web site.  
URL : <http://itself.sec.samsung.co.kr>

## 3. Electrical Parts List

### 3-1 SP47W3HF1X/BOB

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
<b>REMOCON</b>							
1	BP59-00008A	REMOCON; TM65A, COMMOANDO, J54A, 49/L GRAY,		1	AA65-30104B	CLAMP-WIRE; ALL MODEL, NYLON 66, V2, -, BLK, W	
1	6005-001004	SCREW-WOOD; HH, +, M4, L27, BLK, SWRCH18A		1	AA68-50509A	LABEL-BOX; A/P 90(G), ALL MODEL, -, WHT, L250	
1	AA02-00022A	TAPE ETC; SESA, T0.3, 75, 132, BLK		1	AA68-00344A	LABEL-TRANSFER BOX; -, TF-53B	
1	6003-001019	SCREW-TAPTITE; RH, +, B, M4, L12, ZPC(BLK), SWR		1	AA68-00526A	LABEL-RATING; ART PAPER(90), ALL MODEL, LAM	
1	6003-001026	SCREW-TAPTITE; RH, +, B, M4, L15, ZPC(BLK)		1	AC68-00347A	LABEL-TRANSFER RATING; ALTA RESISTENCI	
1	6005-001005	SCREW-WOOD; HH, +, M4.0, L19, NI PLT, SWRCH18A		1	AA68-00340A	LABEL-WARRANTY; -, -, WHT, 75MM, 20	
1	AA60-00132A	SPACER-COVER, DUST; DP, W3, T0.5, 60-00123B		1	AA68-00345A	LABEL-TRANSFER WARRANTY; -, TF-53B5D	
1	AA60-10011A	SCREW-TAPTITE; -, SWRCH18A, M4, L12, HH, +, PC,		1	AA61-20126A	HOLDER-LEG; -, ABS, -, -, BLK,	
1	AA91-00921A	ASSY-HOLDER, MIRROR; HIPS HB BLK, 47W3		1	AA69-30009C	BAG-SHEET; LDPE, T0.08, W150, L120, -, -,	
1	AA91-00921B	ASSY-HOLDER, MIRROR; HIPS HB BLK, 47W3		1	4301-000120	BATTERY-MN; 1.5V, -, AA, 14.5x50mm, -	
1	AA61-00049B	HOLDER-BOX; -, PP, -, -, NTR, V0, AA61-20285A		1	AA39-00006A	CABLE-RCA; -, RCA, 3000MM, 0.12/10, RED/WHT/Y	
1	AA63-70002A	SHEET; -, PE FOAM, T1.0, -, -, 50G		1	6902-000018	BAG PE; PJTV 42	
1	AA64-02336A	CABINET-BACK, BOT; W3, HIPS, V0, BLK		1	AA68-50523A	LABEL-BACK, DOLBY; A/P 100(G), CW764AHD, DOL	
1	AA64-02224B	CABINET-BACK, TOP; DP, 47W3, HIPS HB, BLK, 64-		1	AA39-30007A	IF-CABLE; -, T100mm, 1365#26	
1	AA64-60449B	INLAY-COVER; SP-434JMFPS, T0.5, 149, 3X69.5		1	6003-001023	SCREW-TAPTITE; RWH, +, B, M3, L10, ZPC(YEL), SW	
1	AA65-30008A	CLAMP-CORD; -, PE HB, -, BLK, -		1	AA68-02415A	CARD-RTF; COLORIT 54 CREMA, MOJO80G, SPA, A	
1	AA67-00165A	MIRROR-FRONT; 47W3, GLASS, 861*677*421, FS		1	AA69-01874A	PALLET; ALL MODEL, WOOD, 800, 1250, 120	
1	AA69-00744L	BAG-SHEET; -, HDPE PE FOAM, T0.015, W1650, H1		1	AC68-00285A	LABEL-TAPE TRANSPARENT; SESA, A/P, T0.3,	
1	AA69-01227B	CUSHION SET; 47W3, EPS C=0.02		1	BP94-00383A	ASSY PCB MISC-CG-AMP; DP, SP43T7HFS, J54A, C	
1	AA69-01298A	PACKING CASE-IN; 47W3, CB H-3 AB, YEL, 1207		1	BP94-00444A	ASSY PCB MISC-SPK TERMINAL; DP, SP47W3HF1S	
1	AA69-01299Q	PACKING CASE-OUT; 47W3, H-3 AB, C3, YEL, J54A		1	BP39-00048A	LEAD CONNECTOR; P55A/SVP-47W3HRT, UL1617#2	
1	AA60-00091N	SPACER-FELT; -, FELT, 70X10, -, -, BLK, T1.0, -		<b>PHANTOM CODE</b>			
1	AA91-00773A	ASSY-BRACKER, MIRROR; DP, 91-00751A 19.5KG,		1	47W3HF1X	PHANTOM CODE; PJTV 47 C2.0	
<b>ASSY-C/FRONT, BOT</b>				2	BP96-00103B	ASSY CABINET WOOD; PJTV 47 C2.0	
1	AA91-00775J	ASSY-C/FRONT, BOT; DP, 64-02063Q, 47W3		2	6001-000137	SCREW-MACHINE; BH, +, M3, L8, ZPC(YEL), SM20C,	
2	AA64-02063Z	CABINET-FRONT, BOT; 47W3, HIPS HB, GRAY, SVM1		2	AA61-00972B	HOLDER-SCREEN, R; 47H1, ABS HB, GRAY	
2	AA61-00791B	HOLDER-FRONT, BOT; W3, ABS HB, L40, BLK, D		2	AA64-02225B	CABINET-BACK, SIDE; DP, 47.55W3, HIPS HB, BLK	
2	AA61-01068A	HOLDER-CABINET, BOT(B); W3, ABS HB, L40, BLK,		2	AA67-00196A	AA95-00714B70*612, T=0.73, P=0.52	
2	AA64-02205B	BADGE-DECORATION; W3, NI+AL FORGING+NI, RS		2	AA67-00196C	SCREEN-FRESNEL; 47W, 1072*614, T=1.6, DNP-D	
2	BP96-00127A	ASSY COVER P-HOLDER, CONTROL; DP, W3, ABS HB		2	AA67-00136A	SUN SCREEN-AG; 47W, -, T=82%, 1072*614*2, -, -	
2	6003-001019	SCREW-TAPTITE; RH, +, B, M4, L12, ZPC(BLK), SWR		2	AA63-60131A	SPACER-FELT; SVP403J, FELT, -, -, BLK, T0.5,	
2	AA61-00785B	GUIDE-KNOB, POWER; W3, ABS HB, BLK, C		2	AA91-00824E	ASSY-C/FRONT, MASK; DP, 02058F 22KG, 47W3	
2	AA61-00786B	HOLDER-CONTROL; W3, ABS HB, WHT, SV104M		3	AA64-02058P	CABINET-FRONT, MASK; 47W3, HIPS HB, G4309, SV	
2	AA61-60003J	SPRING-CS; -, SUS304, -, -, OD6,		3	AA64-02211B	BADGE-BRAND; 72MM, AL FORGING, SVM1-126PS, S	
2	AA64-02080B	KNOB POWER; W3, ABS HB WHT, SV104M		3	AA63-00063A	SPACER-DUAL, LOCK; #400, -, -, 19X19, SVP-614J	
2	AA64-02081B	KNOB-CH, VOL; W3, ABS HB, BLK, CH		3	AA61-00974A	HOLDER-MASK; 47H1, HIPS HB, BLK	
2	AA64-02082B	WINDOW-RMC, LED; W3, PC, CLEAR		2	BP95-00147D	ASSY SUB PCB-SENSOR; DP, P54A, SENSOR	
1	BP91-00245W	ASSY CHASSIS; SP47W3HF1S/XEF, J54A, C2.0		2	0203-001329	TAPE-OPP MASKING; ANT-300P, T0.07, W15.0, L5	
1	BP94-00238A	ASSY PCB MISC-VM; DP, HCM4215W3S/XAA, P55A		2	BP73-00004A	RUBBER-CAP; 42W5, SILICONE, WHT, RUBBER	
1	BP94-00137E	ASSY PCB MISC-SUB AMP; 0		2	AA73-00005B	RUBBER-CAP; FLAT, PRJ, SILICONE RUBBER, WHT	
<b>ASSY PCB CRT PCB</b>				2	0203-000402	TAPE-KRAFT; KRAFT, T0.17, W18, L50, BLK	
1	BP94-00257A	ASSY PCB CRT PCB; DP, SP42W5HFS/XEF, J54A		2	AA91-00774E	ASSY DOOR, RACK; DP, W3, HB GRAY, 64-02066	
2	BP59-00005A	MODULE-FOCUS PACK ASS; Y; PJT TV, F301-P03A		3	AA64-02066C	DOOR-RACK; 47.55.65W3, HIPS HB, GRAY, SV808	
2	AA39-20577B	LEAD CONNECTOR ASSY; P54A/SVP-55W3HD, UL16		3	AA64-02206B	WINDOW-DOOR; W3, GLASS, T3.0, BR	
1	BP94-00134Q	ASSY PCB MISC-CONTROL; DP, SP47W3HF1S/XEF,		3	AA91-00758A	ASSY-HINGE, DOOR(R); SPRING, SECC T1.6 W3, W	
1	AA96-20130A	ASSY-POWER, CORD; -, CP2/NO(4.0R), H/C150, KJ		3	BP61-00128A	BRACKET-DOOR; DP, 47W3, AA61-00856B	
1	0201-001059	ADHESIVE-SIL; #9590, WHT, -, CARTRIDGE		3	AA61-00782B	BRACKET-MAGNET; W3, SPC, T2.0, FZW	
1	AA26-00101A	TRANS FBT; FWZ50A001E/FFA97513B, 12KV, 5P-		3	6003-001019	SCREW-TAPTITE; RH, +, B, M4, L12, ZPC(BLK), SWR	
1	AA40-00050A	TUNER; TCLW3101PD18A(S), TCLW3101PD18A(S),		2	6005-001003	SCREW-WOOD; HH, +, M4, L19, ZPC(BLK), SWRCH18A	
1	AA40-00051A	TUNER; TCPW3001PC18B(S), TCPW3001PC18B(S),		2	BP94-00134S	ASSY PCB MISC-A/V FRONT; DP, SP47W3HF1S/XE	
1	AA63-10002A	BAND-TIE; -, NYLON66 V2, -, -, L100, NTR, -		<b>ASSY CPT-R</b>			
1	AA65-30013A	CLAMP-WIRE; -, NYLON-6		1	BP91-00728A	ASSY CPT-R; SP47W3HF1S/XEF, J54A, C2.0	
1	AA65-30018A	CLAMP-WIRE; DONG-A, NYLON-66, -, -, DATL-60		2	BP61-00079A	HOLDER-DY; PJTV, T0.5, NYLON66 V2	
				2	AA91-00735B	ASSY-BRKT, CRT; DP, AA91-00722A, PROJ	
				2	AA63-00076B	SPACER-LENS; FELT, W7, BLK, T0.8	
				2	AA61-00810B	HOLDER-CAP; PROJ, PC, CLR	
				2	AA61-00809B	HOLDER-CRT; PROJ, PC/ABS GF 20%, BLK	

Loc. No.	Code No.	Description ; Specification	Remark
2	AA61-00056B	BRACKET-LENS:PROJECTION,SECC,T1.6,-,-,-,	
2	AA60-00127B	SPACER-LENS:PROJ,SILICONE,D/GRAY	
2	AA60-00126B	SPACER-CAP:PROJ,EPDM,BLK	
2	AA60-00125B	SPACER-CRT:PROJ,SILICONE,D/GRAY	
2	AA39-00018A	LEAD CONNECTOR-ASSY;UL1015#22,UL/CSA,1P	
2	AA33-00016A	MAGNET CONVERGENCE;JH 92LT - 29F,-,29.1M	
2	AA27-00278A	DEFLECTION YOKE;-PT-S0712AC,S/S,PJTCRT(	
2	AA26-30006F	FLYBACK;*WIRE*-FWZ-50A001C,55,30KV	
2	0204-001148	ETHYLENE GLYCOL:MS-S02,CH20HCH20H,80,20	
2	0203-001303	TAPE-ACETATE:#1554,TO.25MM,W19MM,L30M,WH	
2	0201-001030	ADHESIVE-SIL:SE9178,GRY,NON-FLOW,UL94V0	
2	AA61-00845A	CASE-COUPLER,R:DP,PROJ,AA61-00806B	
2	AA03-00307A	CRT MONO:P160DU11RJA S,-,-,-,90%,-,FLA	
2	AA67-00157A	LENS;DELTA 240,RED,C-ELEMENT	
2	AA67-00145A	LENS-ASSY;DELTA 250,CLEAR A/B	
2	AA60-10011A	SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	

### ASSY CPT-G

1	BP91-00729A	ASSY CPT-G:SP47W3HF1S/XEF,J54A,C2.0	
2	BP61-00079A	HOLDER-DY;PJTV,TO.5,NYLON66 V2	
2	AA91-00735B	ASSY-BRKT,CRT:DP,AA91-00722A,PROJ	
2	AA63-00076B	SPACER-LENS:FELT,W7,BLK,TO.8	
2	AA61-00810B	HOLDER-CAP:PROJ,PC,CLR	
2	AA61-00809B	HOLDER-CRT:PROJ,PC/ABS GF 20%,BLK	
2	AA61-00056B	BRACKET-LENS:PROJECTION,SECC,T1.6,-,-,-,	
2	AA60-00127B	SPACER-LENS:PROJ,SILICONE,D/GRAY	
2	AA60-00126B	SPACER-CAP:PROJ,EPDM,BLK	
2	AA60-00125B	SPACER-CRT:PROJ,SILICONE,D/GRAY	
2	AA39-00018A	LEAD CONNECTOR-ASSY;UL1015#22,UL/CSA,1P	
2	AA27-00278A	DEFLECTION YOKE;-PT-S0712AC,S/S,PJTCRT(	
2	AA26-30006F	FLYBACK;*WIRE*-FWZ-50A001C,55,30KV	
2	0204-001148	ETHYLENE GLYCOL:MS-S02,CH20HCH20H,80,20	
2	0203-001303	TAPE-ACETATE:#1554,TO.25MM,W19MM,L30M,WH	
2	0201-001030	ADHESIVE-SIL:SE9178,GRY,NON-FLOW,UL94V0	
2	AA61-00846A	CASE COUPLER G:DP,PROJ,AA61-00807B	
2	AA03-00308A	CRT MONO:P160DU11GHA S,-,-,-,90%,-,FLA	
2	AA67-00158A	LENS;DELTA 240,GREEN,C-ELEMENT	
2	AA67-00145A	LENS-ASSY;DELTA 250,CLEAR A/B	
2	AA60-10011A	SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	

### ASSY CPT-B

1	BP91-00730A	ASSY CPT-B:SP47W3HF1S/XEF,J54A,C2.0	
2	BP61-00079A	HOLDER-DY;PJTV,TO.5,NYLON66 V2	
2	AA91-00735B	ASSY-BRKT,CRT:DP,AA91-00722A,PROJ	
2	AA63-00076B	SPACER-LENS:FELT,W7,BLK,TO.8	
2	AA61-00810B	HOLDER-CAP:PROJ,PC,CLR	
2	AA61-00809B	HOLDER-CRT:PROJ,PC/ABS GF 20%,BLK	
2	AA61-00056B	BRACKET-LENS:PROJECTION,SECC,T1.6,-,-,-,	
2	AA60-00127B	SPACER-LENS:PROJ,SILICONE,D/GRAY	
2	AA60-00126B	SPACER-CAP:PROJ,EPDM,BLK	
2	AA60-00125B	SPACER-CRT:PROJ,SILICONE,D/GRAY	
2	AA39-00018A	LEAD CONNECTOR-ASSY;UL1015#22,UL/CSA,1P	
2	AA33-00018A	MAGNET CONVERGENCE;JH 92LT - 36F,-,29.1M	
2	AA27-00278A	DEFLECTION YOKE;-PT-S0712AC,S/S,PJTCRT(	
2	AA26-30006F	FLYBACK;*WIRE*-FWZ-50A001C,55,30KV	
2	0204-001148	ETHYLENE GLYCOL:MS-S02,CH20HCH20H,80,20	
2	0203-001303	TAPE-ACETATE:#1554,TO.25MM,W19MM,L30M,WH	
2	0201-001030	ADHESIVE-SIL:SE9178,GRY,NON-FLOW,UL94V0	
2	AA61-00847A	CASE-COUPLER,B:DP,PROJ,AA61-00808B	
2	AA03-00309A	CRT MONO:P160DU11BEA S,-,-,-,90%,-,FLA	
2	AA67-00156A	LENS;DELTA 240,CLEAR,C-ELEMENT	
2	AA67-00145A	LENS-ASSY;DELTA 250,CLEAR A/B	
2	AA60-10011A	SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	
1	AA65-30105A	CLAMPER CORE-WIRE:ALL MODEL,NYLON 66,V2,	
1	BP94-00239A	ASSY PCB MISC-DY-JACK:DP,HCM4215W3S/XAA,	
1	BP68-00092A	MANUAL USERS:SP4377HF,BG,W/P100G,J54A,B5	
1	AA63-10007B	BAND-PP:W18,CLEA	
1	AA68-01070A	LABEL-MODEL;-A/P;-30,20,-,-,-,ALL MODE	
1	AA61-01134A	HOLDER-MIRROR,BOT;43,54T6,HIPS HB,BLK	

Loc. No.	Code No.	Description ; Specification	Remark
1	BP96-00103A	ASSY CABINET WOOD; SVP-47W3HRT,P55	
2	BP64-00083A	CABINET-WOOD:SVP-47W3HRT,47W3,WOOD	
2	AA61-00097A	HOLDER-WIRE;-NYLON 6/6,-,-,-,NTR,-	
2	AA60-00078B	SPACER-DUAL,LOCK:W3,#250,19*40	
2	AA60-10051A	SCREW-WOOD;-SWRCH18A,M4,L16,PH,+,-,-,ZP	
2	AA60-10051B	SCREW-WOOD;-SWRCH18A,M3.5,L11,RH,+,-,-,	
2	AA61-00094C	HOLDER-RAIL:PCJ533R,ABS,-,-,-,BLK,HB,480	
2	AA61-00723A	HOLDER-PIN,DABO:PRJT,WOODEN NAIL,OD6XL20	
2	AA61-00507B	HOLDER-CABINET,WOOD;43,54,62J8,ABS,-,-,-	
2	BP61-00075A	HOLDER-JERSEY,ASSY:W3,ABS V0,GRAY,63-000	
2	AA61-00616B	HOLDER-CRT,MAIN:54J7,DP,-,-,-,AA61-005	
2	AA61-01117B	HOLDER-SENSOR:W3,PC VIOLET	
2	AA61-00864A	HOLDER-PCB:W3,HIPS,V0,BLK	
2	AA61-00458B	CASTER;-TP4020-05 PLY,-,OH56,-,-,SR4	
2	AA61-00973B	HOLDER-SCREEN,L:47H1,ABS HB,GRAY	
2	BP61-00087A	RAIL-DOOR,R:W3,ABS HB,BLK	
2	BP61-00087B	RAIL-DOOR,L:W3,ABS HB,BLK	
2	AA61-00857B	BRACKET-NUT,INSERT:W3,M3 ZN	
2	AA61-00858B	BRACKET-FRAME:W3,SECC,T2.0	
2	AA61-10247A	BRACKET-FOCUS:S46DS,SECC,T1.0,-,-,-,-	
2	AA63-00384A	COVER-DUCT:DP 54J8,-,-,-,HB;-AA63-003	
2	AA65-00017A	CLAMP CORE-WIRE:ALL MODEL,NYLON6.6,BLK	
2	AA91-00750A	ASSY-MAGNET,PUSH; MAGNET,W3	
2	6005-001006	SCREW-WOOD:FH,+M3,L15.0,ZPC(BLK),SWRCH1	
2	AA60-10050Y	SCREW-WOOD;-SWRCH18A,M4,L40,FH,+,-,-,ZP	
2	AA61-00999A	HOLDER-DUAL,LOCK:W3,W1,ABS HB,BLK	
2	AA61-20219A	HOLDER-FRONT,BOT,E;-ABS,HB,L40,BLK	
2	AA61-01070A	HOLDER-CABINET,BOT(D);W3,ABS HB,L990,BLK	
2	AA61-00975A	HOLDER-CABINET,BOT-F:W3,ABS HB,GRAY	
2	BP63-00001A	SHEET-EMI:55W3,PS V2+AL LAMI,TO.35,350*	
2	AA61-00792C	HOLDER-SENSOR:W3,ABS HB,BLK	
2	AA61-00971A	HOLDER-SCREEN,TB;47H1,ABS HB,GRAY	
2	AA61-01067A	HOLDER-CABINET,BOT(A);W3,ABS HB,L40,BLK,	
2	3001-001107	SPEAKER;20W,8ohm,95dB,1300Hz	
2	3001-001134	SPEAKER;30W,8ohm,93dB,60Hz	
2	AA39-00086A	LEAD CONNECTOR-ASSY;2.2UF,REC,REC,200MM	
2	AA98-00049B	ASSY-LEAD,CON;-LEAD-CON,CORE,AA39-20505	
2	AA39-00284A	LEAD CONNECTOR-ASSY:SVP-47W3HD,UL2547#26	
2	AA61-00617B	BRACKET-CRT,MAIN:DP;54J7,AA61-00475B	
2	6006-001094	SCREW-ASS'Y WOOD:WW,HH,+M7,L32,ZPC(YEL)	
2	AA61-00618C	GUIDE-FLOW:54J8,-J7,ABS,IVORY,V0	
2	AA91-00766A	ASSY-CENTER,SPK;-W3	
3	AA61-00859A	PLATE-CENTER,SPK;W3,WOOD	
3	3001-000151	SPEAKER;20W,8ohm,92dB,130Hz	
3	AA39-20609A	LEAD CONNECTOR-ASSY;2P,SMH250-02,REC,40	
3	AA60-10051B	SCREW-WOOD;-SWRCH18A,M3.5,L11,RH,+,-,-,	

### ASSY CABINET WOOD

You can search for the updated part code through ITSELF web site.  
URL : <http://itself.sec.samsung.co.kr>

## 3-2 SP42W4HBX/XEU

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
<b>ASSY COVER FRONT</b>				<b>ASSY COVER REAR</b>			
1	M0001	BP90-00119B ASSY COVER FRONT:SP42W4HPX/XEU,J54A		...	T0165	AA64-02743A BADGE-DECORATION:42W5,AL,NL,RS	
..2	T0081	6003-001023 SCREW-TAPTITE:RH,+,B,M3,L10,ZPC(YEL),SW	S.N.A	...	CIS4	BP73-00001A RUBBER-SHEET:42W5,NBB RUBBER,GRAY,10*20	
..2	T0081	6003-001339 SCREW-TAPTITE:HH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A	...	BP02-00003A	CHEMICALS-PTFE SPRAY:P/C34235,ROCOL,DRY	S.N.A
..2	HC+CW	6005-001003 SCREW-WOOD:HH,+,M4,L19,ZPC(BLK),SWRCH18A	S.N.A	..2	T0154	BP91-00752A ASSY-PANNEL,CONTROL;HIPS HB,G4309,SV012	
..2	HC+CW	6005-001003 SCREW-WOOD:HH,+,M4,L19,ZPC(BLK),SWRCH18A	S.N.A	...	T0081	6003-001019 SCREW-TAPTITE:RH,+,B,M4,L12,ZPC(BLK),SWR	
..2	HC+CW	6005-001003 SCREW-WOOD:HH,+,M4,L19,ZPC(BLK),SWRCH18A	S.N.A	...	T0081	6003-001019 SCREW-TAPTITE:RH,+,B,M4,L12,ZPC(BLK),SWR	
..2	HC+CW	6005-001003 SCREW-WOOD:HH,+,M4,L19,ZPC(BLK),SWRCH18A	S.N.A	...	T0081	6003-001019 SCREW-TAPTITE:RH,+,B,M4,L12,ZPC(BLK),SWR	
..2	BCM+CW	6006-001094 SCREW-ASSY WOOD:WW,HH,+,M7,L32,ZPC(YEL)	S.N.A	...	AA61-01132A	VELCRO-A:COMMANDO,BST1 1/4H	S.N.A
..2	AA60-00072B	SPACER-COVER,DUST:43,54,62J9,SPONGE 94HF	S.N.A	...	AA61-01133A	VELCRO-B:COMMANDO,BST1 1/4H	S.N.A
..2	T0081	AA60-10011A SCREW-TAPTITE;-,SWRCH18A,M4,L12,HH,+,PC,	S.N.A	...	AA61-20129A	HOLDER-WIRE;-,NYLON-66,-,-,-,NTR,DAFC-25	S.N.A
..2	T0081	AA60-10011A SCREW-TAPTITE;-,SWRCH18A,M4,L12,HH,+,PC,	S.N.A	...	CIS7	AA61-60003J SPRING ETC-CS;-SUS304,-,-,OD6,N7,OD6,-,	S.N.A
..2	T0115	AA61-00475B BRACKET-CRT,MAIN:54,SECC,T1.6,-,-,-,-	S.N.A	...	AA63-10002A	BAND-TIE:NYLON66 V2,L100,NTR	S.N.A
..2	AA61-00618C	GUIDE-FLOW:54J8,J7,ABS,IVORY,V0	S.N.A	...	BP61-00108A	GUIDE-KONB,CONTROL:42W4,G3676,42W4,ABS H	S.N.A
..2	AA63-10002A	BAND-TIE:NYLON66 V2,L100,NTR	S.N.A	...	BP64-00076A	KNOB CONTROL:42W4,ABS HB G3676	S.N.A
..2	T0056	AA67-00193A SCREEN-TINT:42W,958*550,T=0.7,P		...	BP64-00077A	KNOB POWER:42W4,ABS HB G3676	
..2	T0053	AA67-00193B SCREEN FRESNEL:42W,960*552,T=2.0		...	BP64-00078A	WINDOW REMOCOON-LED:42W4,PC,42W4,PC,CLEAR,S.N.A	
..2	BH73-60304C	RUBBER-SUPPORT:DP15LT,CR V0,GRAY,-,14*7*	S.N.A	...	BP64-00095A	CABINET-PANEL-CONTROL:42W4,HIPS,HB,G4309	S.N.A
..2	T0118	BP26-00004A TRANS FBT-H/V DISTRIBUTOR:FUW50A002B,PJC		<b>ASSY COVER REAR</b>			
..2	T0076	BP39-00009A LEAD CONNECTOR-ASSY:P54A/SVP-42W5,UL2547		1	M0002	BP90-00120A ASSY COVER REAR:SP42W4HPS/XEF,P55A	S.N.A
..2	BP61-00117B	BRACKET-SCREEN,ASSY(TOP):42W5,SECC,T1.0,	S.N.A	..2	T0081	6003-001022 SCREW-TAPTITE:RH,+,B,M3,L12,ZPC(BLK),SWR	S.N.A
...	AA60-00091J	SPACER-FELT;-FELT,330X10,-,-,BLK,T0.5,-	S.N.A	..2	T0081	6003-001026 SCREW-TAPTITE:RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
...	BP61-00043B	HOLDER-SENSOR:W9,PC HB,VIOLET	S.N.A	..2	T0081	6003-001026 SCREW-TAPTITE:RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
...	BP61-00052A	HOLDER-WIRE:PJTV,NYLON,66,NATURAL	S.N.A	..2	T0081	6003-001026 SCREW-TAPTITE:RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
...	BP61-00118A	BRACKET-SCREEN,TB:42W5,SECC,T1.0,SCREEN	S.N.A	..2	T0081	6003-001026 SCREW-TAPTITE:RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	BP61-00119B	BRACKET-SCREEN,ASSY(BOT):42W5,SECC,T1.0,	S.N.A	..2	HC+CW	6005-001003 SCREW-WOOD:HH,+,M4,L19,ZPC(BLK),SWRCH18A	S.N.A
...	AA60-00091J	SPACER-FELT;-FELT,330X10,-,-,BLK,T0.5,-	S.N.A	..2	HC+CW	6005-001003 SCREW-WOOD:HH,+,M4,L19,ZPC(BLK),SWRCH18A	S.N.A
...	AA65-00020A	CLAMPER CORE-WIRE:55W9,NYLON 66	S.N.A	..2	T0112	AA64-02728A CABINET-BACK, TOP:42W5,HIPS,HB,G4309	
...	BP61-00043B	HOLDER-SENSOR:W9,PC HB,VIOLET	S.N.A	..2	T0112	AA64-02729A CABINET-BACK,BOT:42W5,HIPS,V2,G4309	
...	BP61-00052A	HOLDER-WIRE:PJTV,NYLON,66,NATURAL	S.N.A	..2	AA64-60449B	INLAY-COVER:SP-434JMF,PS,T0.5,149.3X69.5	S.N.A
...	BP61-00118A	BRACKET-SCREEN,TB:42W5,SECC,T1.0,SCREEN	S.N.A	..2	AA65-30008A	CLAMPER CORE-CORD;-PE,HB,-,BLK,-	S.N.A
..2	BP61-00120A	BRACKET-SCREEN,ASSY(R):42W5,SECC,T1.0,SC	S.N.A	..2	T0108	AA67-00204B MIRROR-BACK:42W5,SSM,870*633*446	
...	BP61-00052A	HOLDER-WIRE:PJTV,NYLON,66,NATURAL	S.N.A	..2	T0068	BP61-00008A BRACKET-MIRROR,ASSY:42W5,SECC,T1.0,01123	S.N.A
...	BP61-00121A	BRACKET-SCREEN,RL:42W5,SECC,T1.0,SCREEN	S.N.A	...	AA61-01123A	BRACKET-MIRROR:42W5,SECC,T1.0	S.N.A
...	BP61-00043B	HOLDER-SENSOR:W9,PC HB,VIOLET	S.N.A	...	BP60-00005A	SPACER-SPONGE:42W5,RUBBER-SPONGE,T3	S.N.A
..2	BP61-00122A	BRACKET-SCREEN,ASSY(L):42W5,SECC,T1.0,SC	S.N.A	...	T0092	BP96-00038C ASSY COVER P-TERMINAL,ANT:42W5,HIPS V0,B	S.N.A
...	BP61-00121A	BRACKET-SCREEN,RL:42W5,SECC,T1.0,SCREEN	S.N.A	...	AA64-02837A	INLAY-TERMINAL,PAL:COMMANDO,PS SHEET,T0.	S.N.A
...	BP61-00043B	HOLDER-SENSOR:W9,PC HB,VIOLET	S.N.A	...	AA65-00023A	TERMINAL-BOARD,ANT;HIPS V0,BLK	S.N.A
...	AA65-00020A	CLAMPER CORE-WIRE:55W9,NYLON 66	S.N.A	<b>ASSY PRT</b>			
...	BP61-00052A	HOLDER-WIRE:PJTV,NYLON,66,NATURAL	S.N.A	1	BP91-00463A	ASSY PRT:SP42W5HPX/XEU,J54A	S.N.A
..2	BP64-00029A	INLAY-SUPPORT:42W5,PS SHEET,T0.5,94V0	S.N.A	..2	T0026	BP91-00453A ASSY CPT-R:SP42W5HPX/XEU,J54A,CRT-R ASSY	
..2	T0102	BP73-00004A RUBBER-CAP:42W5,SILICONE,WHT,RUBBER		...	AA03-00200A	CRT MONO:P16LSG03RJA,FREE,3.30mH,2.20mH,	S.N.A
..2	T0257	BP91-00005D ASSY-CABINET,WOOD;WOOD,MJU,42W5	S.N.A	...	AA26-30006F	TRANS FBT-ANODE CAP ASSY;-FWZ-50A001C,	
...	T0082	3001-001107 SPEAKER:20W,8OHM,95DB,1300HZ		...	AA27-00278A	DEFLECTION YOKE;-PT-S0712AC,S/S,PJTCRT(	
...	T0076	AA39-00086A LEAD CONNECTOR-ASSY;2.2UF,200MM,REC,REC		...	AA33-00016A	MAGNET CONVERGENCE:JH 92LT - 29F,-,29.1M	
...	HC+CW	AA60-10051A SCREW-WOOD;-SWRCH18A,M4,L16,PH,+,,-,ZP	S.N.A	...	AA60-00126B	SPACER-CAP:PROJ,EPDM,BLK	S.N.A
...	AA61-00097A	HOLDER-WIRE;-NYLON 6/6,-,-,-,NTR,-	S.N.A	...	AA60-00127B	SPACER-LENS:PROJ,SILICONE,D/GRAY	S.N.A
...	AA61-00506B	HOLDER-CRT,MAIN:43,54,62J8,HIPS,-,-,-,BL	S.N.A	...	AA60-00128B	SPACER-CRT:PROJ(65),SILICONE,D/GRAY	S.N.A
...	AA61-00508D	HOLDER-JERSEY:W3,ABS V0,GRAY,G4309	S.N.A	...	T0081	AA60-10011A SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+,PC,	S.N.A
...	AA61-00533B	BRACKET-GRILLE:43,54,62J8,SECC-1 ,T0.5,-	S.N.A	...	AA61-00056B	BRACKET-LENS:PROJECTION,SECC,T1.6,-,-,-,	S.N.A
...	AA64-02724A	CABINET-WOOD:42W5,WOOD,SDE8336R	S.N.A	...	AA61-00806B	CASE-COUPLER,R:PROJ,ALDC,T8,BLK	S.N.A
...	AA98-00049A	ASSY-LEAD,CON;-LEAD-CON,CORE,AA39-20505	S.N.A	...	T0114	AA61-00810B HOLDER-CAP:PROJ,PC,CLR	
....4	T0121	3301-001201 CORE-FERRITE:AE,21x11x32mm,1500,280G		...	T0109	AA67-00187A LENS-ASSY:DELTA71,CLEAR A/B	
...	BP61-00019A	HOLDER-PALLET:42W5,HIPS HB,BLK	S.N.A	...	T0051	AA67-00188A LENS:DELTA71,RED C ELEMENT	
...	BP61-00035A	BRACKET-GRILLE:42W5,SECC-1,T1.0	S.N.A	...	T0107	AA91-00722A ASSY-BRKT,CRT;SECC T1.6,PROJ	
...	AA61-00094C	HOLDER-RAIL:PCJ533R,ABS,-,-,-,BLK,HB,480	S.N.A	...	T0072	AA61-00473B BRACKET-CRT:53,SECC,T1.6,-,-,-,-	S.N.A
...	T0082	3001-001353 SPEAKER:25W,8OHM,90DB+/-3DB,60HZ+/-12HZ		...	AA61-00615B	BRACKET-EARTH:54J8,PBS,T0.5,-,-,-,-	S.N.A
..2	T0017	BP91-00006N ASSY-FRONT,MASK;HIPS HB,G4309,SV012P,42		...	AA61-00812A	SPRING ETC-WIRE:PROJ,STS,3.6	S.N.A
...	T0081	6003-001019 SCREW-TAPTITE:RH,+,B,M4,L12,ZPC(BLK),SWR		...	BP61-00091A	HOLDER-CRT:PJTV,PCABS GF20%,BLUE	S.N.A
...	AA61-01133A	VELCRO-B:COMMANDO,BST1 1/4H	S.N.A	...	BP61-00079A	HOLDER-DY;PJTV,T0.5,NYLON66 V2	S.N.A
...	AA64-02727P	CABINET-FRONT,MASK TOP:42W4,HIPS,HB,G430	S.N.A	...	AA63-00076B	SPACER-LENS:FELT,W7,BLK,T0.8	S.N.A
...	T0057	BP64-00177A BADGE-BRAND:ALL,AL,T1.5,70,11.3,BLK,SILI					
...	T0102	BP73-00004A RUBBER-CAP:42W5,SILICONE,WHT,RUBBER					
..2	T0002	BP91-00007E ASSY-FRONT,BOT;HIPS HB,G4309,SV012P+SV7					
...	T0081	6003-001019 SCREW-TAPTITE:RH,+,B,M4,L12,ZPC(BLK),SWR					
...	AA61-01132A	VELCRO-A:COMMANDO,BST1 1/4H	S.N.A				
...	T0016	AA64-02725B CABINET-FRONT,BOT:42W5,HIPS,HB,G4309,SV0					

Loc. No.	Code No.	Description ; Specification	Remark
...3	T0076	AA39-00018A LEAD CONNECTOR-ASSY;UL1015#22,UL/CSA,1P	
...2	T0027	BP91-00454A ASSY CPT-G:SP42W5HPX/XEU,J54A,CRT-G ASSY	
...3	AA03-00201A	CRT MONO:P16LSG03HKA,FREE,3.30mH,2.20mH,	S.N.A
...3	T0117	AA26-30006F TRANS FBT-ANODE CAP ASSY;-FWZ-50A001C,	
...3	T0078	AA27-00278A DEFLECTION YOKE;-PT-S0712AC,S/S,PJTCRT(	
...3	T0076	AA39-00018A LEAD CONNECTOR-ASSY;UL1015#22,UL/CSA,1P	
...3	AA60-00125B	SPACER-CRT:PROJ,SILICONE,D/GRAY	S.N.A
...3	AA60-00126B	SPACER-CAP:PROJ,EPDM,BLK	S.N.A
...3	AA60-00127B	SPACER-LENS:PROJ,SILICONE,D/GRAY	S.N.A
...3	T0081	AA60-10011A SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+,PC,	S.N.A
...3	AA61-00056B	BRACKET-LENS:PROJECTION,SECC,T1.6,-,-,-,-,-	S.N.A
...3	AA61-00807B	CASE-COUPLER,G:PROJ,ALDC,T8,BLK	S.N.A
...3	AA61-00809B	HOLDER-CRT:PROJ,PC/ABS GF 20%,BLK	S.N.A
...3	T0114	AA61-00810B HOLDER-CAP:PROJ,PC,CLR	
...3	T0109	AA67-00187A LENS-ASSY:DELTA71,CLEAR A/B	
...3	T0051	AA67-00189A LENS:DELTA71,GREEN C ELEMENT	
...3	T0107	AA91-00722A ASSY-BRKT,CRT;SECC T1.6,PROJ	
...4	T0072	AA61-00473B BRACKET-CRT:53,SECC,T1.6,-,-,-,-,-	S.N.A
...4	AA61-00615B	BRACKET-EARTH:54J8,PBS,TO.5,-,-,-,-,-	S.N.A
...4	AA61-00812A	SPRING ETC-WIRE:PROJ,STS,3.6	S.N.A
...3	BP61-00079A	HOLDER-DY;PJTV,TO.5,NYLON66 V2	S.N.A
...3	AA63-00076B	SPACER-LENS:FELT,W7,BLK,TO.8	S.N.A
...2	T0028	BP91-00455A ASSY CPT-B:SP42W5HPX/XEU,J54A,CRT-B ASSY	
...3	AA03-00202A	CRT MONO:P16LSG03BMB,FREE,3.30mH,2.20mH,	S.N.A
...3	T0117	AA26-30006F TRANS FBT-ANODE CAP ASSY;-FWZ-50A001C,	
...3	T0078	AA27-00278A DEFLECTION YOKE;-PT-S0712AC,S/S,PJTCRT(	
...3	T0079	AA33-00018A MAGNET CONVERGENCE:JH 92LT - 36F,-29.1M	
...3	T0076	AA39-00018A LEAD CONNECTOR-ASSY;UL1015#22,UL/CSA,1P	
...3	AA60-00126B	SPACER-CAP:PROJ,EPDM,BLK	S.N.A
...3	AA60-00127B	SPACER-LENS:PROJ,SILICONE,D/GRAY	S.N.A
...3	AA60-00128B	SPACER-CRT:PROJ(65),SILICONE,D/GRAY	S.N.A
...3	T0081	AA60-10011A SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+,PC,	S.N.A
...3	AA61-00056B	BRACKET-LENS:PROJECTION,SECC,T1.6,-,-,-,-,-	S.N.A
...3	AA61-00808B	CASE-COUPLER,B:PROJ,ALDC,T8,BLK	S.N.A
...3	T0114	AA61-00810B HOLDER-CAP:PROJ,PC,CLR	
...3	T0109	AA67-00187A LENS-ASSY:DELTA71,CLEAR A/B	
...3	T0051	AA67-00190A LENS:DELTA71,CLEAR C ELEMENT	
...3	T0107	AA91-00722A ASSY-BRKT,CRT;SECC T1.6,PROJ	
...4	T0072	AA61-00473B BRACKET-CRT:53,SECC,T1.6,-,-,-,-,-	S.N.A
...4	AA61-00615B	BRACKET-EARTH:54J8,PBS,TO.5,-,-,-,-,-	S.N.A
...4	AA61-00812A	SPRING ETC-WIRE:PROJ,STS,3.6	S.N.A
...3	BP61-00091A	HOLDER-CRT:PJTV,PCABS GF20%,BLUE	S.N.A
...3	BP61-00079A	HOLDER-DY;PJTV,TO.5,NYLON66 V2	S.N.A
...3	AA63-00076B	SPACER-LENS:FELT,W7,BLK,TO.8	S.N.A

## ASSY FIXING

1	BP91-00807Z	ASSY FIXING;SP43T7HPX/SPL,J54A,CP2	S.N.A
...2	T0081	6003-001023 SCREW-TAPTITE:RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...2	T0081	6003-001023 SCREW-TAPTITE:RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...2	T0081	6003-001023 SCREW-TAPTITE:RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...2	T0076	AA39-20010B LEAD CONNECTOR-ASSY;1P500,YFH800-01,S,	
...2	T0070	AA61-01127A HOLDER-CHASSIS:COMMANDO,HIPS V0,G4309	S.N.A
...2	AA63-10002A	BAND-TIE:NYLON66 V2,L100,NTR	S.N.A
...2	AA65-00011B	CLAMPER CORE-WIRE:ALL MODEL,NYLON 66,V2,	S.N.A
...2	AA65-30018A	CLAMPER CORE-WIRE:DONG-A,NYLON-66,-,-,-	S.N.A
...2	AA65-30104C	CLAMPER CORE-WIRE:ALL MODEL,NYLON 66,V2,	S.N.A
...2	AA65-30110A	CLAMPER CORE-WIRE:ALL MODEL,NYLON 66,V2,	S.N.A
△ ...2	T0066	AA96-20126C ASSY POWER CORD;-EP3/YES(HK),H/C150,MP5	S.N.A
...3	3811-000401	WIRE-PVC CU:BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
...3	AA61-20284A	HOLDER-P:CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A
...3	T0077	AA39-10007X CBF POWER CORD;-EP3/YES(HK),H03VVH2-F,2	
...2	BP39-00047A	LEAD CONNECTOR:P55A/HCM4215W,UL2547#26,U	

## ASSY CHASSIS

1	M0017	BP91-01004A ASSY CHASSIS:SP42W4HBX/XEU,P55A	
...2	T0073	AA94-05967A ASSY PCB MAIN(OPT):SP42W5HP,J54A, ,100HZ	
...3	C701	2401-001068 C-AL:3300uf,20%,50V,GPBK,22x40,10	
...3	CN906	3711-003046 CONNECTOR-HEADER:BOX,9P,1R,2.5MM,STRAIGH	
...3	JA701	3722-000195 JACK-SCART:42P,-,SN,BLK,NO	

Loc. No.	Code No.	Description ; Specification	Remark
...3	L801	AA29-00004A FILTER LINE NOISE;-20UH,3A,AC80-260V,TQ	
...3	AA39-30007A	CBF IF;-T,100mm,1365#26	
...3	CG	AA63-00396B SHIELD CASE-TOP:PRJT,P54A,SPTE,TO.5,-,-,-	S.N.A
...3	MICOM	AA63-00396B SHIELD CASE-TOP:PRJT,P54A,SPTE,TO.5,-,-,-	S.N.A
...3	CG	AA63-00397B SHIELD CASE-BOT:PRJT,P54A,SPTE,TO.5,-,-,-	S.N.A
...3	MICOM	AA63-00397B SHIELD CASE-BOT:PRJT,P54A,SPTE,TO.5,-,-,-	S.N.A
...3	IC801	AA96-00475C ASSY H/S:SILICON-OIL,KA278R09,KA7808,AA6	S.N.A
...4	0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A
...4	T0087	1203-000293 IC-POS.FIXED REG.;7808,TO-220,3P,-,PLAS	
...4	T0123	1203-002003 IC-VOLTAGE REGULATOR:278R09,TO-220,4P,-,	
...4	T0081	6003-000334 SCREW-TAPTITE:RH,+,2S,M3,L6,ZPC(YEL),SWR	
...4	AA62-00066B	HEAT SINK:D2,D3,AL ,T1.0,89,70,-,AA62-00	S.N.A
...4	T0123	1203-001978 IC-VOLTAGE REGULATOR:KA278RA05,TO-220F,4	
...3	IC601	AA96-00623E ASSY H/S:SCREW,MAIN,AA62-00056A,TDA7265,	S.N.A
...4	0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A
...4	T0124	1201-001026 IC-POWER AMP;7265,ZIP,11P;19.6MIL,DUAL,1	
...4	T0081	6003-000334 SCREW-TAPTITE:RH,+,2S,M3,L6,ZPC(YEL),SWR	
...4	AA62-00056A	HEAT SINK-PS;-T1.0,-,41*35*70,D2,-,-,	S.N.A
...3	BP97-00013A	ASSY ROBOT;0,0,0	S.N.A
...4	IC012	1203-000165 IC-POS.ADJUST REG.;78R12,TO-220,4P,-,PL	
...4	CN906	3711-003641 CONNECTOR-HEADER:BOX,12P,1R,2.5mm,STRAIG	
...4	CN906	3711-003973 CONNECTOR-HEADER:BOX,11P,1R,2.5mm,STRAIG	
...4	CN906	3711-003975 CONNECTOR-HEADER:BOX,14P,1R,2.5mm,STRAIG	
...4	BP97-00058A	ASSY AUTO:SP42W5HPS/XEU,J54A	S.N.A
...5	D609	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
...5	D608	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
...5	D607	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
...5	D605	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
...5	D601	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
...5	D604	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
...5	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
...5	DZ016	0403-000700 DIODE-ZENER:TZP33A,33V,31-35V,1W,DO-41,T	
...5	DZ016	0403-001039 DIODE-ZENER:MA2560,56V,52-60V,1W,DO-41,T	
...5	DZ016	0403-001319 DIODE-ZENER:MTZJ4.7C,4.68-4.93V,500mW,DO	
...5	DZ016	0403-001325 DIODE-ZENER:MTZJ15C,14.35-15.09V,500mW,DO	
...5	Q603	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
...5	Q602	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
...5	Q601	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
...5	R125	2001-000007 R-CARBON:3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000008 R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R808	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
...5	R810	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
...5	R125	2001-000273 R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000290 R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000290 R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000290 R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000290 R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000331 R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000508 R-CARBON:220KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000660 R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000739 R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000739 R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000739 R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000739 R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000739 R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000739 R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000812 R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000812 R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-000812 R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R125	2001-001000 R-CARBON:82KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...5	R801	2001-001077 R-CARBON(S):1500OHM,5%,1/2W,AA,TP,2.4X6.4	
...5	R681	2001-001146 R-CARBON(S):4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
...5	R682	2001-001146 R-CARBON(S):4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
...5	R814	2003-001098 R-METAL OXIDE(S):22Kohm,5%,3W,AA,TP,6x16	
...5	R024	2004-001390 R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
...5	R024	2004-001390 R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
...5	R024	2004-001970 R-METAL(S):1.8Kohm,1%,1/2W,AA,TP,6.5x2.5	
...5	R024	2004-001970 R-METAL(S):1.8Kohm,1%,1/2W,AA,TP,6.5x2.5	
...5	R024	2004-001970 R-METAL(S):1.8Kohm,1%,1/2W,AA,TP,6.5x2.5	
...5	R024	2004-002019 R-METAL(S):33Kohm,1%,1/2W,AA,TP,2.5x6.5mm	
...5	R024	2004-002019 R-METAL(S):33Kohm,1%,1/2W,AA,TP,2.5x6.5mm	
...5	C695	2301-000192 C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....5 C694	2301-000192	C-FILM,PEF;1nF,5%,50V,TP;5.3x10mm,5mm		.....5 L114	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C689	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP;7.5x4.0x5.0mm		.....5 L115	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C687	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP;7.5x4.0x5.0mm		.....5 L116	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C682	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP;7.5x4.0x5.0mm		.....5 L117	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP;5x11,5		.....5 L118	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000039	C-AL:1000uF,20%,16V,GP,TP;10x16,5		.....5 L107	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000039	C-AL:1000uF,20%,16V,GP,TP;10x16,5		.....5 L108	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000192	C-AL:1000uF,20%,50V,GP,TP;16x25,7.5		.....5 L109	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000192	C-AL:1000uF,20%,50V,GP,TP;16x25,7.5		.....5 L112	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000302	C-AL:100uF,20%,25V,GP,TP;6.3x11,5		.....5 L111	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000302	C-AL:100uF,20%,25V,GP,TP;6.3x11,5		.....5 L110	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000360	C-AL:100uF,20%,50V,GP,TP;8x11.5,5		.....5 L128	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000360	C-AL:100uF,20%,50V,GP,TP;8x11.5,5		.....5 L129	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000360	C-AL:100uF,20%,50V,GP,TP;8x11.5,5		.....5 L703	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm	
.....5 C701	2401-000471	C-AL:10uF,20%,50V,BP,TP;5x11,5mm		.....5 L127	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm	
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....5 L106	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm	
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....5 L101	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm	
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....5 L104	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm	
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....5 L706	2701-001030	INDUCTOR-AXIAL:43uH,10%,5x14mm	
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....5 L705	2701-001030	INDUCTOR-AXIAL:43uH,10%,5x14mm	
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....5 L606	3301-000287	BEAD-AXIAL:3.5x1.0x6.0mm,1500,2400G	
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....5 L605	3301-000287	BEAD-AXIAL:3.5x1.0x6.0mm,1500,2400G	
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....5 GT01	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....5 GT02	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....5 GT03	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....5 GT04	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....5	BP97-00041A	ASSY SMD:SP42W5HPS/XEU,J54A	S.N.A
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....6DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL	
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....6DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL	
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....6DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL	
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....6DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL	
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....6DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL	
.....5 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP;5x11,5		.....6DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
.....5 C701	2401-000603	C-AL:1uF,20%,50V,GP,TP;5X11,2		.....6DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
.....5 C701	2401-000603	C-AL:1uF,20%,50V,GP,TP;5X11,2		.....6DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
.....5 C701	2401-000603	C-AL:1uF,20%,50V,GP,TP;5X11,2		.....6DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
.....5 C701	2401-000603	C-AL:1uF,20%,50V,GP,TP;5X11,2		.....6DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
.....5 C701	2401-000832	C-AL:220uF,20%,25V,GP,TP;8x11.5,5		.....6DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6Q711	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6Q709	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6Q708	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6Q712	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6Q713	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6Q714	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6Q715	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6Q716	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6Q107	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6Q108	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6Q701	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6Q702	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000962	C-AL:22uF,20%,50V,GP,TP;5x11,5		.....6Q703	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-001192	C-AL:33uF,20%,50V,GP,TP;6.3x11,5		.....6Q707	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-001397	C-AL:470uF,20%,25V,GP,TP;10x16,5		.....6Q706	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000025	C-AL:100uF,20%,16V,GP,TP;6.3x11,5		.....6Q705	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000025	C-AL:100uF,20%,16V,GP,TP;6.3x11,5		.....6Q704	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5 C701	2401-000025	C-AL:100uF,20%,16V,GP,TP;6.3x11,5		.....61C101	0904-001031	IC-I/O SUPPORT CHIP:8574,8BIT,SOP,16P,-	
.....5 C701	2401-000025	C-AL:100uF,20%,16V,GP,TP;6.3x11,5		.....61C106	1001-001177	IC-VIDEO SWITCH:TEA6425D,VIDEO SWITCH ,S	
.....5 C701	2401-000025	C-AL:100uF,20%,16V,GP,TP;6.3x11,5		.....61C106	1001-001177	IC-VIDEO SWITCH:TEA6425D,VIDEO SWITCH ,S	
.....5 C701	2401-002009	C-AL:100uF,20%,16V,GP,TP;6.3x7,5		.....61C605	1001-001178	IC-AUDIO SWITCH:TEA6422D,AUDIO SWITCH ,S	
.....5 C701	2401-002144	C-AL:47uF,20%,16V,GP,TP;5x11,5		.....61C704	1002-001048	IC-A/D&D/A CONVERTER:PCF8591T,8BIT,SOP,1	
.....5 C701	2401-002300	C-AL:47uF,20%,50V,GP,TP;6.3x11,5		.....61C705	1002-001048	IC-A/D&D/A CONVERTER:PCF8591T,8BIT,SOP,1	
.....5 C701	2401-002300	C-AL:47uF,20%,50V,GP,TP;6.3x11,5		.....6DU410	1201-000541	IC-OP AMP:062,SOP,8P,153MIL,DUAL,6V/mV,P	
.....5 C701	2401-002459	C-AL:220uF,20%,25V,LZ,TP;10x16,5		.....6R188	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 C701	2401-002459	C-AL:220uF,20%,25V,LZ,TP;10x16,5		.....6R194	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 C701	2401-002459	C-AL:220uF,20%,25V,LZ,TP;10x16,5		.....6R904	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 C701	2401-002463	C-AL:470uF,20%,16V,GP,TP;8x11.5,5		.....6R101	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 C701	2401-002463	C-AL:470uF,20%,16V,GP,TP;8x11.5,5		.....6R117	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 C701	2401-002619	C-AL:47uF,20%,25V,GP,TP;5x11,5		.....6R129	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 C701	2401-002619	C-AL:47uF,20%,25V,GP,TP;5x11,5		.....6R778	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 C701	2401-002619	C-AL:47uF,20%,25V,GP,TP;5x11,5		.....6R779	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 C701	2401-002619	C-AL:47uF,20%,25V,GP,TP;5x11,5		.....6R196	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 C701	2401-002619	C-AL:47uF,20%,25V,GP,TP;5x11,5		.....6R798	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 L105	2701-000106	INDUCTOR-AXIAL:1.5uH,10%,3x7mm		.....6R170	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 L113	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		.....6R195	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	

## Electrical Parts List

[illegible]

Loc. No.	Code No.	Description ; Specification	Remark
.....6R648	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R797	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R798	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R750	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R688	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R755	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R771	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R774	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R780	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R181	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R182	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R183	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R184	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R604	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R611	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R748	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R746	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R768	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R769	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R770	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R191	2007-000092	R-CHIP:15Kohm,5%,1/10W,TP,1608	
.....6R190	2007-000092	R-CHIP:15Kohm,5%,1/10W,TP,1608	
.....6R176	2007-000092	R-CHIP:15Kohm,5%,1/10W,TP,1608	
.....6R185	2007-000092	R-CHIP:15Kohm,5%,1/10W,TP,1608	
.....6R741	2007-000093	R-CHIP:20Kohm,5%,1/10W,TP,1608	
.....6R744	2007-000093	R-CHIP:20Kohm,5%,1/10W,TP,1608	
.....6R716	2007-000097	R-CHIP:47Kohm,5%,1/10W,TP,1608	
.....6R704	2007-000097	R-CHIP:47Kohm,5%,1/10W,TP,1608	
.....6R110	2007-000098	R-CHIP:56Kohm,5%,1/10W,TP,1608	
.....6R105	2007-000098	R-CHIP:56Kohm,5%,1/10W,TP,1608	
.....6R612	2007-000134	R-CHIP:33Kohm,5%,1/10W,TP,1608	
.....6R607	2007-000134	R-CHIP:33Kohm,5%,1/10W,TP,1608	
.....6R609	2007-000329	R-CHIP:11Kohm,5%,1/10W,TP,1608	
.....6R608	2007-000329	R-CHIP:11Kohm,5%,1/10W,TP,1608	
.....6R109	2007-000828	R-CHIP:39Kohm,1%,1/10W,TP,1608	
.....6R104	2007-000828	R-CHIP:39Kohm,1%,1/10W,TP,1608	
.....6R753	2007-001010	R-CHIP:51Kohm,5%,1/10W,TP,1608	
.....6R751	2007-001010	R-CHIP:51Kohm,5%,1/10W,TP,1608	
.....6R610	2007-001010	R-CHIP:51Kohm,5%,1/10W,TP,1608	
.....6R605	2007-001010	R-CHIP:51Kohm,5%,1/10W,TP,1608	
.....6R726	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R723	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R721	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R715	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R714	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R727	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R799	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R792	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R789	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R731	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R729	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R713	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R131	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R130	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R121	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R120	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R119	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R118	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R135	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R712	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R710	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R701	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R136	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R173	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R702	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R174	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R717	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R719	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6R613	2007-001179	R-CHIP:8.2Kohm,5%,1/10W,TP,1608	
.....6R606	2007-001179	R-CHIP:8.2Kohm,5%,1/10W,TP,1608	
.....6C120	2203-000236	C-CERAMIC,CHIP:0.1NF,5%,50V,COG,TP,1608	
.....6C120	2203-000236	C-CERAMIC,CHIP:0.1NF,5%,50V,COG,TP,1608	
.....6C120	2203-000236	C-CERAMIC,CHIP:0.1NF,5%,50V,COG,TP,1608	
.....6C120	2203-000236	C-CERAMIC,CHIP:0.1NF,5%,50V,COG,TP,1608	
.....6C120	2203-000236	C-CERAMIC,CHIP:0.1NF,5%,50V,COG,TP,1608	
.....6C120	2203-000236	C-CERAMIC,CHIP:0.1NF,5%,50V,COG,TP,1608	
.....6C120	2203-000236	C-CERAMIC,CHIP:0.1NF,5%,50V,COG,TP,1608	
.....6C120	2203-000236	C-CERAMIC,CHIP:0.1NF,5%,50V,COG,TP,1608	



[illegible]



[illegible]

Loc. No.	Code No.	Description ; Specification	Remark	
.....5	PL02	3301-001324	BEAD-SMD:-,15,-,600,TP,-,0.1	
.....5	IC15	3301-001324	BEAD-SMD:-,15,-,600,TP,-,0.1	
.....5	IC14	3301-001324	BEAD-SMD:-,15,-,600,TP,-,0.1	
.....5	EL09	3301-001324	BEAD-SMD:-,15,-,600,TP,-,0.1	
.....5	IC104	0801-000662	IC-CMOS LOGIC:74HC123,MULTIVIBATOR,SOP,1	
.....5	FC53	2007-000068	R-CHIP:470Kohm,5%,1/8W,TP,2012	
.....5	FC06	2402-000209	C-AL,SMD:22uF,20%,16V,WT,TP5,3x5.3mm,1	
.....5	FC52	2007-000819	R-CHIP:390Kohm,5%,1/10W,TP,1608	
.....5	C120	2203-000681	C-CERAMIC,CHIP:0.027NF,5%,50V,COG,TP,160	
.....5	ER01	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	ER14	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	ER70	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	ER71	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	ER72	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	EC35	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	EC36	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	EC37	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	ER03	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	ER08	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	ER09	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	ER10	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	ER11	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	ER15	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	ER16	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5	SR73	2007-000259	R-CHIP:1.6Kohm,5%,1/10W,TP,1608	
.....5	CL07	2703-000398	INDUCTOR-SMD:10uH,10%,3.2x2.5x2.2mm	
.....5	ER26	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....5	ER27	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....5	ER28	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....5	C120	2203-000896	C-CERAMIC,CHIP:4.7nF,10%,50V,X7R,TP,1608	
.....5	FR68	2007-000107	R-CHIP:470Kohm,5%,1/10W,TP,1608	
.....5	FR69	2007-000107	R-CHIP:470Kohm,5%,1/10W,TP,1608	
.....5	FR83	2007-000104	R-CHIP:150Kohm,5%,1/10W,TP,1608	
.....5	C120	2203-001140	C-CERAMIC,CHIP:68nF,10%,16V,X7R,TP,1608,	
.....5	0	AA41-00610E	PCB:HCM4215W,PCB,4L,E,1.6,162*223,140*10	S.N.A
.....5		0202-001167	SOLDER-CREAM:RX3603-2330HQ,S45A,PASTE,SN	S.N.A
.....4	FC59	2305-000704	C-FILM,MPEF:100nF,5%,250V,TP,16.5x10.3x5	
.....4		0202-000187	SOLDER-WIRE FLUX:-,RS605,D1.2,63Sn/37PB	S.N.A
.....4	FC48	2305-000011	C-FILM,MPEF:470nF,5%,250V,TP,21.5X13.0X7	
.....3	T0104	AA95-02001L	ASSY SUB-PCB MICOM:SP42W5HPX/XEU,J54A,MA	
.....4	T0083	0402-002274	DIODE-RECTIFIER:UF4004,400V,1A,DO-41,TP	
.....4	Q409	0505-000109	FET-SILICON:2N7000,N,60V,200mA,5ohm,400m	
.....4	Q409	0505-000109	FET-SILICON:2N7000,N,60V,200mA,5ohm,400m	
.....4	IC904	1203-001943	IC-VOL. DETECTOR:7025,10,92,3P,-,PLASTIC	
.....4	X901	2801-004071	CRYSTAL-UNIT:6MHZ,30PPM,28-AAM,20PF,400H	
.....4	CN902	3703-001175	CONNECTOR-BACK PANEL:64P,2R,MALE,ANGLE,A	
.....4		AA97-07276A	ASSY SMD:1	S.N.A
.....5	D905	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....5	D906	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....5	D920	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....5	D923	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....5	D602	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....5	D901	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....5	D902	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....5	DZ016	0403-001375	DIODE-ZENER:RLZ3.6B,3.6-3.845V,500mW,LL-	
.....5	DZ016	0403-001375	DIODE-ZENER:RLZ3.6B,3.6-3.845V,500mW,LL-	
.....5	DZ016	0403-001375	DIODE-ZENER:RLZ3.6B,3.6-3.845V,500mW,LL-	
.....5	DZ016	0403-001375	DIODE-ZENER:RLZ3.6B,3.6-3.845V,500mW,LL-	
.....5	DZ016	0403-001375	DIODE-ZENER:RLZ3.6B,3.6-3.845V,500mW,LL-	
.....5	DZ016	0403-001375	DIODE-ZENER:RLZ3.6B,3.6-3.845V,500mW,LL-	
.....5	DZ016	0403-001375	DIODE-ZENER:RLZ3.6B,3.6-3.845V,500mW,LL-	
.....5	Q920	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5	Q908	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5	Q902	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5	Q914	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5	Q915	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5	Q916	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....5	IC112	1103-000180	IC-EEPROM:24C16,2Kx8Bit,SOP,8P,150ML,10	
.....5	T0087	1203-002302	IC-POSIFIXED REG:78RM33D,D-PAK,3P,-,PL	
.....5	IC901	1204-001912	IC-DECODER:SDA5550M,P-MOFP,100P,-,PLASTI	
.....5	R964	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	R960	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	R959	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	R965	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....5	R940	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....5	R969	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....5	R970	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	

## Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
....5 R972	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		....5 C950	2402-000179	C-AL,SMD:47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....5 R907	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		....5 C936	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	
....5 R909	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		....5 C921	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	
....5 R916	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		....5 C918	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	
....5 R918	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		....5 C915	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	
....5 R939	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		....5 C913	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	
....5 R923	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		....5 C917	2402-001049	C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.4	
....5 R922	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		....5 C912	2402-001049	C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.4	
....5 R988	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		....5 C911	2402-001049	C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.4	
....5 R952	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		....5 L905	2703-001245	INDUCTOR-SMD:8.2uH,10%,2x1.25x1.25mm	
....5 R953	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		....5 L904	3301-001324	BEAD-SMD:-,15-,600,TP,-,0.1	
....5 R917	2007-000076	R-CHIP:330ohm,5%,1/10W,TP,1608		....5 L907	3301-001324	BEAD-SMD:-,15-,600,TP,-,0.1	
....5 R911	2007-000076	R-CHIP:330ohm,5%,1/10W,TP,1608		....5 L920	3301-001324	BEAD-SMD:-,15-,600,TP,-,0.1	
....5 R963	2007-000077	R-CHIP:470ohm,5%,1/10W,TP,1608		....5 L903	3301-001324	BEAD-SMD:-,15-,600,TP,-,0.1	
....5 R901	2007-000077	R-CHIP:470ohm,5%,1/10W,TP,1608		....5 L902	3301-001324	BEAD-SMD:-,15-,600,TP,-,0.1	
....5 R930	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		....5 L901	3301-001324	BEAD-SMD:-,15-,600,TP,-,0.1	
....5 R933	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		....5 R945	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
....5 R936	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		....5 R946	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
....5 R974	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		....5 R948	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
....5 R905	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		....5 R949	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
....5 R921	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		....5 R950	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
....5 R924	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		....5 R951	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
....5 R925	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		....5 PCB	AA41-00599B	PCB-MICOM:HCM4215W,FR,4.2L,B,1.6T,180X24	S.N.A
....5 R915	2007-000081	R-CHIP:2.7Kohm,5%,1/10W,TP,1608		....5	0202-001167	SOLDER-CREAM:RX3603-2330HO,S45A,PASTE,SN	S.N.A
....5 R958	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....4 IC902	1102-001130	IC-EPROM:M27W201-80F6,256KX8BIT,DIP,32P	
....5 R971	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....4	0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A
....5 R976	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....3	0202-001167	SOLDER-CREAM:RX3603-2330HO,S45A,PASTE,SN	S.N.A
....5 R978	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....3	0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A
....5 R955	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....3 CN902	3703-001187	CONNECTOR-BACK PANEL:64P,2R,FEMALE,STRAI	
....5 R903	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....3 JA705	3722-001802	JACK-PIN:2P,8.3PI,NI,WHIT/RED,-	
....5 R904	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....3 JA702	3722-000183	JACK-SCART:21P,4mm,SN,BLK,NO	
....5 R906	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....3 IC106	1001-000223	IC-VIDEO SWITCH:TEA5114A,-,DIP,16P,334MI	
....5 R908	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....3 IC802	1203-000119	IC-NEGA.FIXED REG.:7905,TO-220,3P,-,PLAS	
....5 R927	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....3 C701	2401-000737	C-AL:2200uF,20%,50V,GP,TP,18x35.5,7	
....5 R928	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....3 L802	AA27-10001C	COIL CHOKE:-,100uH,K,-,5.0A,ST,700UH-K(R	
....5 R954	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....3 TU02	AA40-00051A	TUNER:TCPW3001PC18B(S),TCPW3001PC18B(S),	
....5 R934	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....3 X601	2801-004020	CRYSTAL-UNIT:18.432MHz,30ppm,28-AAM,12pF	
....5 R985	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....3 T0093	BP95-00153A	ASSY SUB PCB-COMV MOD:J54A,C1.5	
....5 R986	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		....4	0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A
....5 R957	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608		....4 L01	2701-001030	INDUCTOR-AXIAL:43uH,10%,5x14mm	
....5 R944	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608		....4 CN902	3703-001124	CONNECTOR-BACK PANEL:32P,2R,MALE,ANGLE,A	
....5 R919	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608		....4 CN906	3711-003601	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,ANGLE,	
....5 R987	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608		....4	AA97-14194A	ASSY SMD:,PAL	S.N.A
....5 R926	2007-000097	R-CHIP:47Kohm,5%,1/10W,TP,1608		....5	0202-001167	SOLDER-CREAM:RX3603-2330HO,S45A,PASTE,SN	S.N.A
....5 R975	2007-000121	R-CHIP:820ohm,5%,1/10W,TP,1608		....5 D13	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 R941	2007-000123	R-CHIP:1.5Kohm,5%,1/10W,TP,1608		....5 D12	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 R914	2007-000123	R-CHIP:1.5Kohm,5%,1/10W,TP,1608		....5 D11	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 R962	2007-000583	R-CHIP:22Kohm,1%,1/10W,TP,1608		....5 D10	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 R966	2007-000710	R-CHIP:3.9KOHM,5%,1/10W,DA,TP,2012		....5 D14	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 R961	2007-000939	R-CHIP:47Kohm,1%,1/10W,TP,1608		....5 D15	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....5 D16	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....5 D17	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....5 D18	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....5 D01	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....5 D02	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....5 D03	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....5 D04	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....5 D05	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....5 D09	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....5 D08	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....5 D07	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....5 D06	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....5 DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
....5 C120	2203-000189	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....5 DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
....5 C120	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216		....5 DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
....5 C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,1608		....5 Q03	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
....5 C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,1608		....5 Q02	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
....5 C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,1608		....5 Q04	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
....5 C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,1608		....5 Q10	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
....5 C120	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012		....5 Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.	
....5 C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,1608		....5 Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.	
....5 C120	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-		....5 Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.	
....5 C120	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-		....5 IC104	0801-002345	IC-CMOS LOGIC:7S04,INVERTER,SOT-353,5P,4	
....5 C120	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		....5 IC104	0801-002345	IC-CMOS LOGIC:7S04,INVERTER,SOT-353,5P,4	
....5 C120	2203-000748	C-CERAMIC,CHIP:0.03nF,5%,50V,COG,TP,2012		....5 IC104	0801-002345	IC-CMOS LOGIC:7S04,INVERTER,SOT-353,5P,4	
....5 C120	2203-000748	C-CERAMIC,CHIP:0.03nF,5%,50V,COG,TP,2012		....5 IC08	1001-000164	IC-ANALOG MULTIPLEX:74HC4052,CMOS,SOP,16	
....5 C120	2203-005809	C-CERAMIC,CHIP:1000nF,10%,16V,X7R,TP,201		....5 IC13	1001-001155	IC-ANALOG MULTIPLEX:NC7S3157P6X,CMOS,SC	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....5 IC112	1103-001195	IC-EEPROM:24C64,8Kx8Bit,SOP,8P,150MIL,10		.....5 R60	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 DU410	1201-001135	IC-OP AMP:324,SOP,ST,14P,150MIL,QUAD,100		.....5 R55	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 DU410	1201-001504	IC-OP AMP:072,SOP,8P,150MIL,DUAL,-,PLAST		.....5 R54	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 DU410	1201-001504	IC-OP AMP:072,SOP,8P,150MIL,DUAL,-,PLAST		.....5 R79	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 DU410	1201-001504	IC-OP AMP:072,SOP,8P,150MIL,DUAL,-,PLAST		.....5 R78	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 DU410	1201-001504	IC-OP AMP:072,SOP,8P,150MIL,DUAL,-,PLAST		.....5 R73	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 T0074	1201-001520	IC-VIDEO AMP:EL2250CS,SOIC,8P,150MIL,DUA		.....5 R72	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 IC03	1203-001824	IC-VOL. DETECTOR:7042,SOT-89,3P,-,PLASTI		.....5 R67	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 T0087	1203-002302	IC-POS.FIXED REG.:78RM33D,D-PAK,3P,-,PL		.....5 R49	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 IC17	1209-001163	IC-PLL:TLC2932PWLE,SOP,14P,-,PLASTIC		.....5 R08	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 R36	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,2012		.....5 R07	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 R35	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,2012		.....5 R06	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 R31	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,2012		.....5 R04	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 R30	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,2012		.....5 R01	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 R143	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608		.....5 R48	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 R144	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608		.....5 R133	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 R25	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608		.....5 R121	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 R122	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608		.....5 R119	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 R123	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608		.....5 R118	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....5 R141	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608		.....5 R86	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....5 R136	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608		.....5 R92	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....5 R15	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608		.....5 R93	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....5 R24	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608		.....5 R96	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....5 R45	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608		.....5 R97	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....5 R46	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608		.....5 R85	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....5 R09	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608		.....5 R113	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....5 R10	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608		.....5 R114	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....5 R129	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608		.....5 R115	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....5 R134	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608		.....5 R83	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....5 R135	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608		.....5 R84	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....5 R59	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		.....5 R125	2007-000091	R-CHIP:12Kohm,5%,1/10W,TP,1608	
.....5 R65	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		.....5 R05	2007-000102	R-CHIP:100Kohm,5%,1/10W,TP,1608	
.....5 R71	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		.....5 R127	2007-000109	R-CHIP:1Mohm,5%,1/10W,TP,1608	
.....5 R77	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		.....5 R100	2007-000118	R-CHIP:390ohm,5%,1/10W,TP,1608	
.....5 R91	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		.....5 R32	2007-000119	R-CHIP:560ohm,5%,1/10W,TP,1608	
.....5 R53	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		.....5 R34	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....5 R02	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		.....5 R29	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....5 R16	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		.....5 R28	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....5 R17	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		.....5 R117	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....5 R20	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		.....5 R107	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....5 R47	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608		.....5 R33	2007-000124	R-CHIP:2.2Kohm,5%,1/10W,TP,1608	
.....5 R62	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R120	2007-000124	R-CHIP:2.2Kohm,5%,1/10W,TP,1608	
.....5 R64	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R90	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608	
.....5 R68	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R89	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608	
.....5 R58	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R88	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608	
.....5 R56	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R87	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608	
.....5 R52	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R108	2007-000381	R-CHIP:13Kohm,5%,1/10W,TP,1608	
.....5 R70	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R139	2007-000402	R-CHIP:150ohm,5%,1/10W,TP,1608	
.....5 R98	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R138	2007-000402	R-CHIP:150ohm,5%,1/10W,TP,1608	
.....5 R94	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R137	2007-000402	R-CHIP:150ohm,5%,1/10W,TP,1608	
.....5 R82	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R99	2007-000704	R-CHIP:3.6Kohm,5%,1/16W,DA,TP,1608	
.....5 R80	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R95	2007-000704	R-CHIP:3.6Kohm,5%,1/16W,DA,TP,1608	
.....5 R76	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R126	2007-000857	R-CHIP:4.3Kohm,1%,1/10W,TP,1608	
.....5 R74	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R27	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5 R38	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R26	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5 R37	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R148	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....5 R110	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 R116	2007-001179	R-CHIP:8.2Kohm,5%,1/10W,TP,1608	
.....5 R11	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 RN04	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP,8P,TP	
.....5 R101	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 RN05	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP,8P,TP	
.....5 R03	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 RN06	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP,8P,TP	
.....5 R39	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 RN01	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP,8P,TP	
.....5 R50	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 RN02	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP,8P,TP	
.....5 R44	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 RN03	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP,8P,TP	
.....5 R43	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 C120	2203-000041	C-CERAMIC,CHIP:0.01NF,0.25PF,50V,COG,TP,	
.....5 R42	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 C120	2203-000041	C-CERAMIC,CHIP:0.01NF,0.25PF,50V,COG,TP,	
.....5 R41	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 C120	2203-000041	C-CERAMIC,CHIP:0.01NF,0.25PF,50V,COG,TP,	
.....5 R40	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608		.....5 C120	2203-000041	C-CERAMIC,CHIP:0.01NF,0.25PF,50V,COG,TP,	
.....5 R128	2007-000079	R-CHIP:1.8Kohm,5%,1/10W,TP,1608		.....5 C120	2203-000041	C-CERAMIC,CHIP:0.01NF,0.25PF,50V,COG,TP,	
.....5 R81	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608		.....5 C120	2203-000041	C-CERAMIC,CHIP:0.01NF,0.25PF,50V,COG,TP,	
.....5 R75	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608		.....5 C120	2203-000041	C-CERAMIC,CHIP:0.01NF,0.25PF,50V,COG,TP,	
.....5 R69	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608		.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	
.....5 R51	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608		.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	
.....5 R57	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608		.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	
.....5 R63	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608		.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	
.....5 R109	2007-000082	R-CHIP:3.3Kohm,5%,1/10W,TP,1608		.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	
.....5 R66	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	
.....5 R61	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608		.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	

## Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		.....5 T0119	AA09-00032A	IC MICOM:TSC87251G2D-24IB,TSC87251G2D-OT	S.N.A
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		.....5 PCB	AA41-00717E	PCB:Convergence,FR,4,4,1,6T,245*245,90*1	S.N.A
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		.....5 IC125	BP13-00003A	IC ASIC:SDC12,128,-0.3 TO +3.8,0 TO 70,Q	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		..2 T0098	AA94-08268A	ASSY PCB MISC-VM:COMMANDO	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		..3 RZ120	2008-001097	R-FUSIBLE(S):330HM,5%,1/2W,AC,BK,2.5X6.5	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		..3	AA97-07230M	ASSY AUTO-VM:COMMANDO	S.N.A
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 DZ106	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 DZ105	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 DZ102	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 QZ103	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 QZ106	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 QZ105	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 QZ104	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 RZ122	2001-000019	R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4MM	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 R125	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 R125	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 R125	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 R125	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 R125	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 R125	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 R125	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 R125	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 R125	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 R125	2001-000554	R-CARBON:270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 R125	2001-000666	R-CARBON:330HM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 R125	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 RZ110	2001-001100	R-CARBON(S):2.70HM,5%,1/2W,AA,TP,2.4X6.4	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 RZ104	2001-001100	R-CARBON(S):2.70HM,5%,1/2W,AA,TP,2.4X6.4	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 RZ105	2001-001139	R-CARBON(S):39KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 RZ106	2001-001139	R-CARBON(S):39KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 RZ103	2003-000713	R-METAL OXIDE(S):47ohm,5%,2W,AF,TP,4x12m	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 RZ111	2003-000713	R-METAL OXIDE(S):47ohm,5%,2W,AF,TP,4x12m	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 RZ123	2003-002157	R-METAL OXIDE:220OHM,5%,2W,AG,TP,6X16MM	
.....5 C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,		....4 RZ113	2003-002157	R-METAL OXIDE:220OHM,5%,2W,AG,TP,6X16MM	
.....5 C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608		....4 RZ112	2003-002157	R-METAL OXIDE:220OHM,5%,2W,AG,TP,6X16MM	
.....5 C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608		....4 RFZ101	2008-001086	R-FUSIBLE(S):3.3ohm,5%,2W,AG,TP,3.9x12mm	
.....5 C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608		....4 C598	2201-000193	C-CERAMIC,DISC:0.01nF,0.25PF,50V,COG,TP,	
.....5 C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,1608		....4 C598	2201-000193	C-CERAMIC,DISC:0.01nF,0.25PF,50V,COG,TP,	
.....5 C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,1608		....4 C598	2201-000516	C-CERAMIC,DISC:4.7nF,+100-0%,500V,Y5U,TP	
.....5 C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,1608		....4 C598	2201-000516	C-CERAMIC,DISC:4.7nF,+100-0%,500V,Y5U,TP	
.....5 C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,1608		....4 C598	2201-000604	C-CERAMIC,DISC:0.056nF,+100-0%,500V,SL,T	
.....5 C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,1608		....4 C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
.....5 C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,1608		....4 C701	2401-000832	C-AL:220uF,20%,25V,GP,TP,8x11,5,5	
.....5 C120	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-		....4 C701	2401-001157	C-AL:33uF,20%,160V,GP,TP,12.5x20,5	
.....5 C120	2203-000575	C-CERAMIC,CHIP:220nF,10%,25V,X7R,TP,2012		....4 C701	2401-001220	C-AL:4.7uF,20%,160V,GP,TP,8x11,5,5	
.....5 C120	2203-000575	C-CERAMIC,CHIP:220nF,10%,25V,X7R,TP,2012		....4 C701	2401-001220	C-AL:4.7uF,20%,160V,GP,TP,8x11,5,5	
.....5 C120	2203-000975	C-CERAMIC,CHIP:47nF,10%,25V,X7R,TP,1608,		....4 C701	2401-001513	C-AL:47uF,20%,16V,WT,TP,5x11,5	
.....5 C120	2203-000975	C-CERAMIC,CHIP:47nF,10%,25V,X7R,TP,1608,		....4 C701	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
.....5 C120	2203-000975	C-CERAMIC,CHIP:47nF,10%,25V,X7R,TP,1608,		....4 LZ101	2701-000002	INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm	
.....5 C120	2203-001071	C-CERAMIC,CHIP:0.056nF,5%,50V,COG,TP,160		....4 CN906	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH	
.....5 C120	2203-001071	C-CERAMIC,CHIP:0.056nF,5%,50V,COG,TP,160		....4 CN906	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH	
.....5 C120	2203-001071	C-CERAMIC,CHIP:0.056nF,5%,50V,COG,TP,160		....4 CN906	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH	
.....5 C120	2203-001071	C-CERAMIC,CHIP:0.056nF,5%,50V,COG,TP,160		....4 PCB	AA41-00611A	PCB-VM:HCM4215W,FR-1,1LA,1.6T,245X245,P	S.N.A
.....5 C120	2203-001071	C-CERAMIC,CHIP:0.056nF,5%,50V,COG,TP,160		....4 RZ114	2003-000458	R-METAL OXIDE(S):100ohm,5%,2W,AF,TP,4x12	
.....5 C120	2203-001071	C-CERAMIC,CHIP:0.056nF,5%,50V,COG,TP,160		..3 QZ101	AA96-00243M	ASSY H/S:-,AMP,AA62-000450A,2SA1011,HERC	S.N.A
.....5 C120	2203-001071	C-CERAMIC,CHIP:0.056nF,5%,50V,COG,TP,160		....4	0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A
.....5 C120	2203-001083	C-CERAMIC,CHIP:0.005nF,0.1pF,50V,NP0,TP,		....4 T0090	0502-000131	TR-POWER:2SA1011-D,PNP,1.2W,TO-220,-,60	
.....5 C120	2203-001083	C-CERAMIC,CHIP:0.005nF,0.1pF,50V,NP0,TP,		....4 T0081	6003-000335	SCREW-TAPTITE:RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
.....5 C120	2203-001083	C-CERAMIC,CHIP:0.005nF,0.1pF,50V,NP0,TP,		....4	AA62-00045A	HEAT SINK-PS-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
.....5 C120	2203-001083	C-CERAMIC,CHIP:0.005nF,0.1pF,50V,NP0,TP,		..3 QZ102	AA96-00243L	ASSY H/S:-,CRT,AA62-000450A,2SC2344,HERC	S.N.A
.....5 C120	2203-001245	C-CERAMIC,CHIP:0.082nF,5%,50V,NP0,TP,201		....4	0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A
.....5 C120	2203-001245	C-CERAMIC,CHIP:0.082nF,5%,50V,NP0,TP,201		....4 T0090	0502-000153	TR-POWER:2SC2344-D,NPN,1.2W,TO-220,-,60	
.....5 C120	2203-001245	C-CERAMIC,CHIP:0.082nF,5%,50V,NP0,TP,201		....4 T0081	6003-000335	SCREW-TAPTITE:RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
.....5 C38	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4		....4	AA62-00045A	HEAT SINK-PS-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
.....5 C40	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4		..3	0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A
.....5 C70	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4		..3 T0121	3301-001201	CORE-FERRITE:AE,21x11x32mm,1500,280G	
.....5 C84	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4		..3 T0079	AA33-00017A	MAGNET CONVERGENCE:JH 92LT - 29G,-,29.1M	
.....5 C14	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4		..3 T0081	6003-001023	SCREW-TAPTITE:RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
.....5 C06	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4		..3 T0076	AA39-20055C	LEAD CONNECTOR-ASSY:6P,500,YBNH025-06,6	
.....5 C03	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4		..2 T0105	AA94-08270A	ASSY PCB MISC-DY JACK:COMMANDO	
.....5 C01	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4		..3	AA97-07230N	ASSY AUTO:COMMANDO	S.N.A
.....5 C80	2402-001049	C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.4		....4 R301	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4	
.....5 OSC01	2804-001479	OSCILLATOR-ClOCK:24MHZ,100PPM,50PF,TP,5V		....4 R302	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4	
.....5 EF03	3301-001324	BEAD-SMD:-,15,-,600,TP,-,0.1		....4 R303	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4	
.....5 EF04	3301-001324	BEAD-SMD:-,15,-,600,TP,-,0.1		....4 PCB	AA41-00632A	PCB-DY CONNECTION:HCM4215W,FR-1,1LA,1.6	S.N.A

Loc. No.	Code No.	Description ; Specification	Remark
...3	0202-000187	SOLDER-WIRE FLUX;-RS60S,D1.2,63Sn/37Pb	S.N.A
...3 GT01	AA60-40012D	PIN-GT,ASSY:T1.6,6-12.5-.NYLON66	S.N.A
...3 GT05	AA60-40012D	PIN-GT,ASSY:T1.6,6-12.5-.NYLON66	S.N.A
...3 GT09	AA60-40012D	PIN-GT,ASSY:T1.6,6-12.5-.NYLON66	S.N.A
...3 GT13	AA60-40012D	PIN-GT,ASSY:T1.6,6-12.5-.NYLON66	S.N.A
...3	AA61-01197A	HOLDER-PCB,DY:COMANDO,ABS V0,BLK	S.N.A
..2 T0065	BP94-00041A	ASSY PCB CRT:SP42W5HPX,J54A	S.N.A
...3	0202-000187	SOLDER-WIRE FLUX;-RS60S,D1.2,63Sn/37Pb	S.N.A
...3 VR561	2101-000321	VR-ROTARY:1Mohm,-0.6W,SIDE	
...3 VR531	2101-000321	VR-ROTARY:1Mohm,-0.6W,SIDE	
...3 VR501	2101-000321	VR-ROTARY:1Mohm,-0.6W,SIDE	
...3 V561	3704-001019	SOCKET-CRT:10P,29.1PI,35.5PI,AU30U,-	
...3 V531	3704-001019	SOCKET-CRT:10P,29.1PI,35.5PI,AU30U,-	
...3 V501	3704-001019	SOCKET-CRT:10P,29.1PI,35.5PI,AU30U,-	
...3 CN906	3711-002645	CONNECTOR-HEADER:BOX,6P,1R,2.5mm,STRAIGH	
...3 CN906	3711-002648	CONNECTOR-HEADER:BOX,9P,1R,2.5mm,STRAIGH	
...3 CN906	3711-003052	CONNECTOR-HEADER:BOX,10P,1R,2.5MM,STRAIGH	
...3 CN906	3711-003052	CONNECTOR-HEADER:BOX,10P,1R,2.5MM,STRAIGH	
...3 CN906	3711-003973	CONNECTOR-HEADER:BOX,11P,1R,2.5mm,STRAIGH	
...3 CN906	3711-003973	CONNECTOR-HEADER:BOX,11P,1R,2.5mm,STRAIGH	
...3 SG301	4715-001050	SURGE ABSORBER:2.4kV,20%,1500A,-DISC-RA	
...3 SG562	AA27-00084A	COIL:S-23,-,S-23,5000Mohm MIN,	
...3 SG532	AA27-00084A	COIL:S-23,-,S-23,5000Mohm MIN,	
...3 SG502	AA27-00084A	COIL:S-23,-,S-23,5000Mohm MIN,	
...3 T0076	AA39-00112A	LEAD CONNECTOR-ASSY,UL1007#26,UL/CSA,10	
...3 T0076	AA39-00120F	LEAD CONNECTOR-ASSY:SIR-T165,UL1007#26,U	
...3 T0076	AA39-00198D	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL1617	
...3 T0076	AA39-20010B	LEAD CONNECTOR-ASSY,1P,500,YFH800-01,S,	
...3 T0076	AA39-20010D	LEAD CONNECTOR-ASSY,1P,400,YFH800-01,S,	
...3 T0076	AA39-20010D	LEAD CONNECTOR-ASSY,1P,400,YFH800-01,S,	
...3 T0076	AA39-20027B	LEAD CONNECTOR-ASSY,6P,400,67096-006,S,	
...3 T0076	AA39-20031D	LEAD CONNECTOR-ASSY,9P,500,67096-009,S,	
...3	AA63-10002A	BAND-TIE:NYLON66 V2,L100,NTR	S.N.A
...3 Q371	AA96-00244H	ASSY H/S:SCREW,2SC4636(2),CRT,SILICON-OIL	S.N.A
...4	0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A
...4 T0090	0502-000442	TR-POWER:2SC4636RB,NPN,2W,TO-220,ST,10-	
...4 T0081	6003-000335	SCREW-TAPTITE:RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
...4	AA62-00046A	HEAT SINK-PS,-,T1.0,-,D1(DREAM) 60X25X	S.N.A
...3 IC561	AA96-50311L	ASSY H/S:-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3 IC531	AA96-50311L	ASSY H/S:-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3 IC501	AA96-50311L	ASSY H/S:-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...4 T0074	1201-001131	IC-VIDEO AMP:6111,SIP9P,-,SINGLE,-,PLAS	
...4 T0081	6003-000334	SCREW-TAPTITE:RH,+,2S,M3,L6,ZPC(YEL),SWR	
...4	AA62-30175D	HEAT SINK-PS,-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
...3 T0076	BP39-00004B	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL3239	
...3 T0076	BP39-00004C	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL3239	
...3 T0076	BP39-00004C	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL3239	
...3 T0103	BP59-00005A	MODULE-FOCUS PACK ASS:Y:PJT TV,F301-P03A	
...3	BP97-00088A	ASSY AUTO:SP42W5HPX,J54A,CRT-PCB-ASSY	S.N.A
...4 D504	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
...4 D509	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
...4 D510	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
...4 D372	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
...4 D361	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
...4 D362	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
...4 D371	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
...4 T0083	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
...4 T0083	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
...4 T0083	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
...4 T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
...4 T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
...4 T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
...4 T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
...4 T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
...4 DZ016	0403-000334	DIODE-ZENER:U2Z.7BSA,2.7V,2.54-2.75V,500	
...4 DZ016	0403-000334	DIODE-ZENER:U2Z.7BSA,2.7V,2.54-2.75V,500	
...4 DZ016	0403-000334	DIODE-ZENER:U2Z.7BSA,2.7V,2.54-2.75V,500	
...4 DZ016	0403-000508	DIODE-ZENER:MTZJ5.6B,5.6V,5.45-5.73V,500	
...4 DZ016	0403-000508	DIODE-ZENER:MTZJ5.6B,5.6V,5.45-5.73V,500	
...4 DZ016	0403-000508	DIODE-ZENER:MTZJ5.6B,5.6V,5.45-5.73V,500	
...4 DZ016	0403-000708	DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
...4 DZ016	0403-000708	DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
...4 DZ016	0403-000708	DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
...4 DZ016	0403-000708	DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
...4 Q563	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
...4 Q534	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	

Loc. No.	Code No.	Description ; Specification	Remark
...4 Q533	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
...4 Q504	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
...4 Q361	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
...4 Q362	0501-000366	TR-SMALL SIGNAL:KSC2330-Y,NPN,1W,TO-92L,	
...4 Q502	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
...4 T0090	0502-000006	TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-	
...4 T0090	0502-000006	TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-	
...4 T0090	0502-000006	TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-	
...4 R125	2001-000006	R-CARBON:2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000007	R-CARBON:3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R584	2001-000028	R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R554	2001-000028	R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R524	2001-000028	R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R580	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R550	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R520	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R577	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R547	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R517	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R366	2001-000109	R-CARBON(S):470OHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R125	2001-000232	R-CARBON:1.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000319	R-CARBON:120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000539	R-CARBON:24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000577	R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000613	R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000613	R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000723	R-CARBON:4.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000908	R-CARBON:62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000908	R-CARBON:62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000908	R-CARBON:62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000938	R-CARBON:680HM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000995	R-CARBON:820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-000995	R-CARBON:820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R125	2001-001015	R-CARBON:9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4 R566	2001-001049	R-CARBON(S):1.3KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R536	2001-001049	R-CARBON(S):1.3KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R506	2001-001049	R-CARBON(S):1.3KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R581	2001-001052	R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R551	2001-001052	R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R521	2001-001052	R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R371	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R370	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R369A	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R367	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R368	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R369	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R567	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
...4 R537	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
...4 R507	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
...4 R381	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
...4 R361	2001-001097	R-CARBON(S):2.4KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R374	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R373	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R372	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R377	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4 R375	2001-001113	R-CARBON(S):270KOHM,5%,1/2W,AA,TP,2.4X6.4	

## Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
....4	R365	2001-001120 R-CARBON(S);3.30HM,5%,1/2W,AA,TP,2.4X6.4		....4	EL03	6042-000002 EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	R574	2001-001122 R-CARBON(S);3.9KOHM,5%,1/2W,AA,TP,2.4X6.		....4	EL563	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R544	2001-001122 R-CARBON(S);3.9KOHM,5%,1/2W,AA,TP,2.4X6.		....4	EL537	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R514	2001-001122 R-CARBON(S);3.9KOHM,5%,1/2W,AA,TP,2.4X6.		....4	EL536	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R583	2002-001006 R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7		....4	EL535	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R582	2002-001006 R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7		....4	EL564	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R553	2002-001006 R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7		....4	EL565	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R552	2002-001006 R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7		....4	EL566	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R522	2002-001006 R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7		....4	EL567	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R523	2002-001006 R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7		....4	EL534	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R559	2002-001015 R-COMPOSITION;47Kohm,5%,1/2W,AA,TP,3.7x9		....4	EL01	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R589	2002-001015 R-COMPOSITION;47Kohm,5%,1/2W,AA,TP,3.7x9		....4	EL02	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R529	2002-001015 R-COMPOSITION;47Kohm,5%,1/2W,AA,TP,3.7x9		....4	EL04	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R575	2002-001017 R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9		....4	EL05	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R545	2002-001017 R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9		....4	EL533	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R515	2002-001017 R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9		....4	EL505	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R579	2002-001021 R-COMPOSITION;560KOHM,5%,1/2W,AA,TP,3.7X		....4	EL504	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R578	2002-001021 R-COMPOSITION;560KOHM,5%,1/2W,AA,TP,3.7X		....4	EL503	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R549	2002-001021 R-COMPOSITION;560KOHM,5%,1/2W,AA,TP,3.7X		....4	GT537	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	R548	2002-001021 R-COMPOSITION;560KOHM,5%,1/2W,AA,TP,3.7X		....4	GT536	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	R519	2002-001021 R-COMPOSITION;560KOHM,5%,1/2W,AA,TP,3.7X		....4	GT535	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	R518	2002-001021 R-COMPOSITION;560KOHM,5%,1/2W,AA,TP,3.7X		....4	GT534	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	R588	2003-000738 R-METAL OXIDE(S);56Kohm,5%,2W,AA,TP,4x12		....4	GT533	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	R538	2003-000738 R-METAL OXIDE(S);56Kohm,5%,2W,AA,TP,4x12		....4	GT561	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	R508	2003-000738 R-METAL OXIDE(S);56Kohm,5%,2W,AA,TP,4x12		....4	GT568	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	R024	2004-001892 R-METAL(S);162Kohm,1%,1/2W,AA,TP,2.5x6.5		....4	GT567	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	R024	2004-001892 R-METAL(S);162Kohm,1%,1/2W,AA,TP,2.5x6.5		....4	GT564	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	R024	2004-001892 R-METAL(S);162Kohm,1%,1/2W,AA,TP,2.5x6.5		....4	GT563	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	R573	2008-000204 R-FUSIBLE(S);0.22ohm,10%,1/2W,AF,TP,2.5x		....4	GT562	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	R543	2008-000204 R-FUSIBLE(S);0.22ohm,10%,1/2W,AF,TP,2.5x		....4	GT501	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	R513	2008-000204 R-FUSIBLE(S);0.22ohm,10%,1/2W,AF,TP,2.5x		....4	GT374	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000119 C-CERAMIC,DISC;100NF,+80-20%,50V,Y5V,TP,		....4	GT373	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000119 C-CERAMIC,DISC;100NF,+80-20%,50V,Y5V,TP,		....4	GT372	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000119 C-CERAMIC,DISC;100NF,+80-20%,50V,Y5V,TP,		....4	GT371	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000556 C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.		....4	GT502	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000599 C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.		....4	GT532	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000599 C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.		....4	GT531	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000599 C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.		....4	GT506	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000723 C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X5		....4	GT504	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000723 C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X5		....4	GT503	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000723 C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X5		....4	GT375	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000983 C-CERAMIC,DISC;1NF,10%,2KV,Y5P,TP,9X5MM,		....4	GT566	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000983 C-CERAMIC,DISC;1NF,10%,2KV,Y5P,TP,9X5MM,		....4	R382	2002-001014 R-COMPOSITION;6.8Kohm,10%,1/2W,AA,TP,3.7	
....4	C598	2201-000983 C-CERAMIC,DISC;1NF,10%,2KV,Y5P,TP,9X5MM,		....4	T0083	0402-000243 DIODE-RECTIFIER;RC2-V1,2000V,0.2A,DO-201	
....4	C565	2305-000149 C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5		....4	C701	2401-000480 C-AL;10uF,20%,50V,GP,TP,5x11.5	
....4	C535	2305-000149 C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5		....4	0	AA41-00600F PCB CRT;SVP-55W3HD,FR-1,1L,F,1.6T,3,P55A	S.N.A
....4	C505	2305-000149 C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5		....3	T0121	3301-001201 CORE-FERRITE;AE,21x11x32mm,1500,280G	
....4	C567	2305-000154 C-FILM,MPEF;100nF,5%,400V,TP,21.5x6.5x11		....2	T0146	BP94-00044A ASSY PCB MISC-SUB;SP42W5HPX,J54A	
....4	C537	2305-000154 C-FILM,MPEF;100nF,5%,400V,TP,21.5x6.5x11		....3	T0083	0402-000250 DIODE-RECTIFIER;RG4C,1000V,1A,-	
....4	C507	2305-000154 C-FILM,MPEF;100nF,5%,400V,TP,21.5x6.5x11		....3	T0083	0402-000542 DIODE-RECTIFIER;RU4AM,600V,2A,-	
....4	C361	2306-000122 C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0mm		....3	T0083	0402-000542 DIODE-RECTIFIER;RU4AM,600V,2A,-	
....4	C701	2401-002075 C-AL;4.7uF,20%,50V,GP,TP,5x11.5		....3	Q409	0505-001116 FET-SILICON;BUZ73A,N,200V,22A,0.6ohm,40W	
....4	C701	2401-002075 C-AL;4.7uF,20%,50V,GP,TP,5x11.5		....3	PC801S	0604-001032 PHOTO-COUPLER;TR,170-260%,300mV,DIP-4,ST	
....4	C701	2401-000133 C-AL;100uF,20%,16V,GP,TP,10x20,5		....3	PC811S	0604-001032 PHOTO-COUPLER;TR,170-260%,300mV,DIP-4,ST	
....4	C701	2401-000302 C-AL;100uF,20%,25V,GP,TP,6.3x11.5		....3	DU410	1201-000191 IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV	
....4	C701	2401-000302 C-AL;100uF,20%,25V,GP,TP,6.3x11.5		....3	DU410	1201-000191 IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV	
....4	C701	2401-000430 C-AL;10uF,20%,250V,GP,TP,10x16mm,5mm		....3	T0123	1203-001006 IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-	
....4	C701	2401-000430 C-AL;10uF,20%,250V,GP,TP,10x16mm,5mm		....3	T0086	1203-002177 IC-PWM CONTROLLER;VIPER12ADIP,DIP,8P,300	
....4	C701	2401-000430 C-AL;10uF,20%,250V,GP,TP,10x16mm,5mm		....3	NT801S	1404-001195 THERMISTOR-NTC;5.1ohm,15%,2900,27mW/C,BK	
....4	C701	2401-000430 C-AL;10uF,20%,250V,GP,TP,10x16mm,5mm		....3	C598	2201-000446 C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
....4	C701	2401-000430 C-AL;10uF,20%,250V,GP,TP,10x16mm,5mm		....3	C598	2201-000446 C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
....4	C701	2401-000430 C-AL;10uF,20%,250V,GP,TP,10x16mm,5mm		....3	C598	2201-000987 C-CERAMIC,DISC;2.2NF,20%,400V,Y5U,TP,12.	
....4	C701	2401-000430 C-AL;10uF,20%,250V,GP,TP,10x16mm,5mm		....3	C598	2201-000987 C-CERAMIC,DISC;2.2NF,20%,400V,Y5U,TP,12.	
....4	C701	2401-001571 C-AL;47uF,+20%-0%,50V,GP,TP,8x11.5,		....3	C414	2301-001338 C-FILM,MPE-PF;0.68NF,5%,1.6KV,BK,28X7X1	
....4	C701	2401-001571 C-AL;47uF,+20%-0%,50V,GP,TP,8x11.5,		....3	C421	2301-001520 C-FILM,PPF;3.9NF,+5%,1.6KV,BK,27X12.5X6	
....4	C701	2401-001571 C-AL;47uF,+20%-0%,50V,GP,TP,8x11.5,		....3	C435	2306-000322 C-FILM,MPPF;12NF,5%,1.6KV,BK,29X20.5X13MM	
....4	C701	2401-001621 C-AL;6.8uF,20%,450V,GP,TP,13x20,5		....3	C701	2401-003076 C-AL;3300UF,20%,50V,WT,BK,18X35.5MM,7.5	
....4	L531	2701-000114 INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		....3	CN906	3711-002645 CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH	
....4	L501	2701-000114 INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm		....3	CN906	3711-003043 CONNECTOR-HEADER;BOX,4P,1R,2.5MM,STRAIGH	
....4	L561	2701-000168 INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm		....3	CN906	3711-003043 CONNECTOR-HEADER;BOX,4P,1R,2.5MM,STRAIGH	
....4	SG533	4715-001036 SURGE ABSORBER;500V,20%,--TP		....3	CN906	3711-003043 CONNECTOR-HEADER;BOX,4P,1R,2.5MM,STRAIGH	
....4	SG561	4715-001036 SURGE ABSORBER;500V,20%,--TP		....3	CN906	3711-003046 CONNECTOR-HEADER;BOX,9P,1R,2.5MM,STRAIGH	
....4	SG563	4715-001036 SURGE ABSORBER;500V,20%,--TP		....3	IC063	AA13-00094A IC HYBRID;-DDRIO01A,SIP,5P,-TP	
....4	SG501	4715-001036 SURGE ABSORBER;500V,20%,--TP		....3	L821	AA27-00218A COIL-PFC;E12820,125UH,190UH,7%,E12820 PL	
....4	SG503	4715-001036 SURGE ABSORBER;500V,20%,--TP		....3	L862	AA27-10001C COIL CHOKE;-100uH,K,-5.0A,ST,700UH-K/R	
....4	SG531	4715-001036 SURGE ABSORBER;500V,20%,--TP		....3	L863	AA27-10001C COIL CHOKE;-100uH,K,-5.0A,ST,700UH-K/R	
....4	EL06	6042-000002 EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A	....3	LB02	AA27-40001S COIL HORIZ. WIDTH;-110uH,SB-5S8202,6,PI	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
...3	LX801S	AA29-30002L FILTER LINE NOISE,-,10mHMIN,5A,AC90-260V		...4	Q301	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
...3	T0076	AA39-00180A LEAD CONNECTOR-ASSY,-,14P,100MM,YBNH250-1		...4	Q460	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
...3	IC204	AA96-00038B ASSY H/S,-,CONVERGENCE,AA62-30173E,STK39	S.N.A	...4	Q462	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
...3	IC203	AA96-00038B ASSY H/S,-,CONVERGENCE,AA62-30173E,STK39	S.N.A	△ ...4	VX801S	1405-000187 VARISTOR:750V,1250A,12.5x7mm,TP	
...4		0205-000129 GREASE-SILICON:SC102,JAPAN	S.N.A	...4	R812	2001-000002 R-CARBON(S):200KOHM,5%,1/2W,AA,TP,6.4X2.	
...4	T0074	1201-001512 IC-VIDEO AMP:392,SIP,22P,-,TRIPLE,-,PLAS		...4	R811	2001-000002 R-CARBON(S):200KOHM,5%,1/2W,AA,TP,6.4X2.	
...4	T0081	6003-001021 SCREW-TAPTITE:RH,+B,M3,L15,ZPC(YEL),SWR	S.N.A	...4	R125	2001-000005 R-CARBON:390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
△ ...4		AA62-30173E HEAT SINK-SS,-,T1.0,WHITE,SCREW-HOLE(1	S.N.A	...4	R125	2001-000008 R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△ ...3	D855	AA96-00243E ASSY H/S,-,SOUND,AA62-00045A,FMG-G26S	S.N.A	...4	R125	2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△ ...3	D856	AA96-00243E ASSY H/S,-,SOUND,AA62-00045A,FMG-G26S	S.N.A	...4	R303	2001-000016 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
...4		0205-000129 GREASE-SILICON:SC102,JAPAN	S.N.A	...4	R836	2001-000052 R-CARBON(S):3.3KOHM,5%,1/2W,AA,TP,2.4X6.	
...4	T0083	0402-000231 DIODE-RECTIFIER:FMG-G26S,600V,4A,TO-220F		...4	R433	2001-000052 R-CARBON(S):3.3KOHM,5%,1/2W,AA,TP,2.4X6.	
...4	T0081	6003-000335 SCREW-TAPTITE:RH,+2S,M3,L8,ZPC(YEL),SWR	S.N.A	...4	RS808	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4		AA62-00045A HEAT SINK-PS,-,T1.0,-,DREAM,-,-,-,-	S.N.A	...4	RS807	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
...3	Q401	AA96-00475B ASSY H/S:SCREW,OIL,AA62-00051B,FJL6920YD	S.N.A	...4	R855	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	T0083	0402-001296 DIODE-RECTIFIER:FMP-3FU,1.5KV,5A,TO-3PF,		...4	R835	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	T0081	6003-000333 SCREW-TAPTITE:RH,+2S,M3,L10,ZPC(YEL),SW	S.N.A	...4	RS803	2001-000085 R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.	
...4		0205-000129 GREASE-SILICON:SC102,JAPAN	S.N.A	...4	R125	2001-000241 R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4		AA60-30001A WASHER-PLATE:M3,ID3.5,15X8.5,T1.0,SBHG	S.N.A	...4	R125	2001-000241 R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4		AA62-00051B HEAT SINK-PS,-,-,SILVER,HOLE 34mm,ALL,	S.N.A	...4	R125	2001-000273 R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△ ...4	T0090	0502-001230 TR-POWER:FJL6920YDTU,N,200000MW,TO-264 F		...4	R125	2001-000290 R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△ ...3	D811S	AA96-00276A ASSY H/S,-,BRIDGE,AA62-00052A,RBV606,WAS	S.N.A	...4	R125	2001-000290 R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4		0205-000129 GREASE-SILICON:SC102,JAPAN	S.N.A	...4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0083	0402-000549 DIODE-BRIDGE:RBV606,600V,6A,-,BK		...4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0081	6003-000335 SCREW-TAPTITE:RH,+2S,M3,L8,ZPC(YEL),SWR	S.N.A	...4	R125	2001-000522 R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4		AA60-30003A WASHER:T1.5,SBHG-1	S.N.A	...4	R125	2001-000563 R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4		AA62-00052A HEAT SINK-PS,-,-,SILVER,HOLE 18.5mm, 2	S.N.A	...4	R125	2001-000563 R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△ ...3	D851	AA96-00475B ASSY H/S:SILICON-OIL,FMLG-12S(4),AA62-00	S.N.A	...4	R125	2001-000563 R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4		0205-000129 GREASE-SILICON:SC102,JAPAN	S.N.A	...4	R125	2001-000563 R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0083	0402-000233 DIODE-RECTIFIER:FML-G12S,200V,5A,-,-		...4	R125	2001-000563 R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	IC012	1203-000165 IC-POS.I.ADJUST REG.:78R12,TO-220,4P,-,PL		...4	R125	2001-000577 R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0081	6003-000334 SCREW-TAPTITE:RH,+2S,M3,L6,ZPC(YEL),SWR		...4	R125	2001-000577 R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4		AA62-00066B HEAT SINK:D2,D3,AL ,T1.0,89.70,-,AA62-00	S.N.A	...4	R125	2001-000591 R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	IC301	AA96-00623A ASSY H/S:-,POWER,AA62-00056A,LA7845	S.N.A	...4	R125	2001-000591 R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4		0205-000129 GREASE-SILICON:SC102,JAPAN	S.N.A	...4	R125	2001-000591 R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0088	1204-000517 IC-VERTICAL DEF:LA7845,SIP,7P,-,PLASTIC		...4	R125	2001-000591 R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0081	6003-000334 SCREW-TAPTITE:RH,+2S,M3,L6,ZPC(YEL),SWR		...4	R125	2001-000591 R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4		AA62-00056A HEAT SINK-PS,-,T1.0,-,41*35*70,D2,-,-	S.N.A	...4	R125	2001-000591 R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△ ...3	TS801S	BP26-00001A TRANS SWITCHING-POWER:19B012,P55A,HCM421		...4	R125	2001-000660 R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△ ...3	T444S	BP26-00005A TRANS FBT:FUW50A003,PJCPT,2.3MH,FEERITE,		...4	R125	2001-000702 R-CARBON:39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3		BP97-00067A ASSY AUTO:SP42W5HPX/XEU,J54A	S.N.A	...4	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	D403	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		...4	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	D302	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		...4	R125	2001-000761 R-CARBON:4300HM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	D407	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		...4	R125	2001-000761 R-CARBON:4300HM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	DS804	0401-000006 DIODE-SWITCHING:BAV21,250V,250mA,DO-35,T		...4	R125	2001-000800 R-CARBON:5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	DS802	0401-000006 DIODE-SWITCHING:BAV21,250V,250mA,DO-35,T		...4	R125	2001-000800 R-CARBON:5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0083	0402-000132 DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		...4	R125	2001-000800 R-CARBON:5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0083	0402-000132 DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		...4	R125	2001-000837 R-CARBON:51KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0083	0402-000132 DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		...4	R125	2001-000857 R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0083	0402-000132 DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		...4	R125	2001-000857 R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0083	0402-000132 DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		...4	R125	2001-000857 R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0083	0402-000254 DIODE-RECTIFIER:RGP10J,600V,1A,DO-41,TP		...4	R125	2001-000857 R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0083	0402-000493 DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L		...4	R125	2001-000857 R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0083	0402-000537 DIODE-RECTIFIER:RH1A,600V,0.6A,DO-204AC		...4	R125	2001-000977 R-CARBON:8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	T0083	0402-000540 DIODE-RECTIFIER:RU20A,600V,1.5A,-,TP		...4	R401	2001-001037 R-CARBON(S):0.39OHM,5%,1/2W,AA,TP,2.4X6.	
...4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		...4	R856	2001-001043 R-CARBON(S):0OHM,5%,1/2W,AA,TP,2.4X6.4MM	
...4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		...4	RS804	2001-001088 R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
...4	T0083	0402-001286 DIODE-RECTIFIER:RP1H,2000V,1A,-,TP		...4	R854	2001-001088 R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
...4	DZ016	0403-000704 DIODE-ZENER:TZP7.5B,7.5V,7.5-8.4V,1W,DO-		...4	R839	2001-001088 R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
...4	DZ016	0403-000716 DIODE-ZENER:MTZJ4.7B,4.7V,4.55-4.8V,500m		...4	R440	2001-001093 R-CARBON(S):2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
...4	DZ016	0403-000720 DIODE-ZENER:MTZJ9.1B,9.1V,8.57-9.01V,500		...4	R437	2001-001093 R-CARBON(S):2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
...4	DZ016	0403-001167 DIODE-ZENER:MTZJ30D,30V,29.02-30.51V,500		...4	R837	2001-001108 R-CARBON(S):22KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	DZ016	0403-001319 DIODE-ZENER:MTZJ4.7C,4.68-4.93V,500mW,DO		...4	RZ109	2001-001114 R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4	
...4	DZ016	0403-001321 DIODE-ZENER:MTZJ6.8C,6.66-7.01V,500mW,DO		...4	RZ108	2001-001114 R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4	
...4	DZ016	0403-001325 DIODE-ZENER:MTZJ15C,14.35-15.09V,500mW,D		...4	RZ107	2001-001114 R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4	
...4	DZ016	0403-001328 DIODE-ZENER:MTZJ22A,20.15-21.20V,500mW,D		...4	RZ104	2001-001114 R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4	
...4	DZ016	0403-001328 DIODE-ZENER:MTZJ22A,20.15-21.20V,500mW,D		...4	RZ105	2001-001114 R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4	
...4	DZ016	0403-001328 DIODE-ZENER:MTZJ22A,20.15-21.20V,500mW,D		...4	RZ106	2001-001114 R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4	
...4	DZ016	0403-001330 DIODE-ZENER:MTZJ30A,26.99-28.39V,500mW,D		...4	RS802	2001-001124 R-CARBON(S):3.90HM,5%,1/2W,AA,TP,2.4X6.4	
...4	DS805	0404-001056 DIODE-SCHOTTKY:RK16,60V,1.5A,DO-204AC,TP		...4	R468	2001-001150 R-CARBON(S):470KOHM,5%,1/2W,AA,TP,2.4X6.	
...4	Q461	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		...4	R407	2001-001153 R-CARBON(S):470HM,5%,1/2W,AA,TP,2.4X6.4M	
...4	Q432	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		...4	R406	2001-001153 R-CARBON(S):470HM,5%,1/2W,AA,TP,2.4X6.4M	
...4	QS802	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		...4	R439	2001-001155 R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
...4	QS801	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		...4	R858	2001-001155 R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
...4	Q851	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		...4	R859	2001-001155 R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
...4	Q482	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		...4	RS806	2001-001168 R-CARBON(S):6.8KOHM,5%,1/2W,AA,TP,2.4X6.	

Loc. No.	Code No.	Description : Specification	Remark
....4	C598	2201-000863	C-CERAMIC,DISC:0.68NF,10%,50V,Y5P,TP,5X3
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP
....4	C689	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP
....4	CZ137	2202-000561	C-CERAMIC,MLC-RADIAL:0.68NF,5%,50V,COG,T
....4	CZ135	2202-000561	C-CERAMIC,MLC-RADIAL:0.68NF,5%,50V,COG,T
....4	CZ116	2202-000561	C-CERAMIC,MLC-RADIAL:0.68NF,5%,50V,COG,T
....4	CZ114	2202-000561	C-CERAMIC,MLC-RADIAL:0.68NF,5%,50V,COG,T
....4	CZ112	2202-000561	C-CERAMIC,MLC-RADIAL:0.68NF,5%,50V,COG,T
....4	C433	2301-000104	C-FILM,PEF:1.2NF,5%,50V,TP,6.5X3.0X5.5MM
....4	C475	2301-000111	C-FILM,PEF:1.8nF,5%,50V,TP,6.5x3.0x5.5mm
....4	C479	2301-000111	C-FILM,PEF:1.8nF,5%,50V,TP,6.5x3.0x5.5mm
....4	CS801	2301-000356	C-FILM,PEF:47nF,5%,50V,TP,7.5x4.0x6.5,5m
....4	C838	2301-000356	C-FILM,PEF:47nF,5%,50V,TP,7.5x4.0x6.5,5m
....4	C477	2301-001067	C-FILM,MPPF:82nF,5%,400V,TP,19x15.5x7.7,
....4	C438	2301-001194	C-FILM,MPPF:470nF,5%,250V,TP,18x16x8,7.5
....4	C831	2301-001216	C-FILM,PPF:47nF,5%,630V,TP,20x14.5x22.7,
....4	CB19	2301-001401	C-FILM,PPF:27nF,5%,630V,TP,19x11x17mm,7,
....4	C415	2303-000331	C-FILM,PPF:4.7nF,5%,630V,TP,19.5x12x7.7,
....4	C311	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5
....4	C417	2305-000178	C-FILM,MPEF:10nF,5%,100V,TP,-,5mm
....4	C304	2305-000285	C-FILM,MPEF:220nF,5%,100V,TP,10.5X5.5X15
....4	C482	2305-001037	C-FILM,MPEF:330nF,5%,63V,TP,7.5x5.5x14.5
....4	C483	2305-001037	C-FILM,MPEF:330nF,5%,63V,TP,7.5x5.5x14.5
....4	C865	2305-000427	C-FILM,MPEF:47nF,5%,100V,TP,7.5x12.5x3.5
....4	C307	2305-000427	C-FILM,MPEF:47nF,5%,100V,TP,7.5x12.5x3.5
....4	C309	2305-000427	C-FILM,MPEF:47nF,5%,100V,TP,7.5x12.5x3.5
....4	C701	2401-000183	C-AL:1000uF,20%,35V,WT,TP,12.5x25,5
....4	C701	2401-000183	C-AL:1000uF,20%,35V,WT,TP,12.5x25,5
....4	C701	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5
....4	C701	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5
....4	C701	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11,5,5
....4	C701	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11,5,5
....4	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5
....4	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5
....4	C701	2401-000493	C-AL:10uF,20%,50V,LZ,TP,5x11mm,5mm
....4	C701	2401-000703	C-AL:2200uF,20%,25V,GP,-,12.5x25mm,
....4	C701	2401-000711	C-AL:2200uF,20%,25V,GP,TP,16x25,7,5
....4	C701	2401-000927	C-AL:22uF,20%,250V,GP,TP,13x20,5
....4	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,5
....4	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,5
....4	C701	2401-001192	C-AL:33uF,20%,50V,GP,TP,6.3x11,5
....4	C701	2401-001363	C-AL:470uF,20%,16V,GP,TP,10x12,5,5
....4	C701	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5
....4	C701	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5
....4	C701	2401-001914	C-AL:1uF,20%,50V,BP,TP,5x11,5
....4	C701	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5
....4	C701	2401-002216	C-AL:2200uF,20%,35V,GP,TP,16x25,7,5
....4	C701	2401-002216	C-AL:2200uF,20%,35V,GP,TP,16x25,7,5
....4	C701	2401-002463	C-AL:470uF,20%,16V,GP,TP,8x11,5,5
....4	LZ110	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm
....4	LZ111	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm
....4	LZ112	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm
....4	LZ103	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm
....4	LZ107	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm
....4	LZ109	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm
....4	F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-
....4	L855	3301-000287	BEAD-AXIAL:3.5x1.0x6.0mm,1500,2400G
....4	L856	3301-000287	BEAD-AXIAL:3.5x1.0x6.0mm,1500,2400G
....4	LB01	3301-000287	BEAD-AXIAL:3.5x1.0x6.0mm,1500,2400G
....4	LB03	3301-000287	BEAD-AXIAL:3.5x1.0x6.0mm,1500,2400G
....4	L851	3301-000287	BEAD-AXIAL:3.5x1.0x6.0mm,1500,2400G
....4	J809	3301-000287	BEAD-AXIAL:3.5x1.0x6.0mm,1500,2400G
....4	L495	3301-000287	BEAD-AXIAL:3.5x1.0x6.0mm,1500,2400G
....4	L857	3301-000287	BEAD-AXIAL:3.5x1.0x6.0mm,1500,2400G
....4	FD801S	3601-000120	FUSE-AXIAL LEAD:125V,2.5A,FAST-ACTING,GL
....4	FD871S	3601-001086	FUSE-AXIAL LEAD:125V,5A,FAST-ACTING,GLAS





Loc. No.	Code No.	Description ; Specification	Remark
....4	R450	2003-000586 R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4	C480	2306-000122 C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m	
....4	C481	2305-000289 C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
....4	C701	2401-001625 C-AL:6.8uF,20%,50V,GP,TP,5x11.5	
△	RR471S	2103-001024 VR-SEMI:50Kohm,25%,0.3W,TOP	
....4	R420	2003-002156 R-METAL OXIDE:560OHM,5%,2W,AG,TP,6X16MM	
....4	R405	2003-002156 R-METAL OXIDE:560OHM,5%,2W,AG,TP,6X16MM	
....4	R305	2003-001036 R-METAL OXIDE(S);3.3ohm,5%,2W,AF,TP,3.9x	
....4	C416	2305-000665 C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C430	2301-000108 C-FILM,PEF:1.5nF,5%,50V,TP,6.5x3.0x5.5mm	
....4	R125	2001-000508 R-CARBON:220KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000569 C-AL:1uF,20%,250V,GP,TP,6.3x11.5	
....4	DZ016	0403-000699 DIODE-ZENER:TZP27B,27V,27-30.8V,1W,DO-41	
....4	DZ016	0403-000699 DIODE-ZENER:TZP27B,27V,27-30.8V,1W,DO-41	
....4	DZ016	0403-000734 DIODE-ZENER:MTZP15B,15V,14.7-16.5V,1W,DO-	
....4	DZ016	0403-000734 DIODE-ZENER:MTZP15B,15V,14.7-16.5V,1W,DO-	
....4	R838	2008-001014 R-FUSIBLE(S):220ohm,5%,1W,AF,TP,3.2x10mm	
....4	C701	2401-003114 C-AL:4.7uF,20%,250V,WT,TP,10x16.5	
....4	R400	2001-003218 R-CARBON(S):0.18ohm,10%,1/2W,AA,TP,2.4x6	
....4	C431	2305-000407 C-FILM,MPEF:470nF,5%,100V,TP,-,5mm	
....4	J438	2701-000176 INDUCTOR-AXIAL:330uH,10%,2.8x7mm	
....4	C701	2401-003058 C-AL:100uF,20%,200V,WT,TP,16x25.7.5	
....4	R438	2001-001178 R-CARBON(S):680OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R125	2001-000755 R-CARBON:430KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000012 R-CARBON:680KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	T0083	0402-001443 DIODE-RECTIFIER:EGP20K,800V,2A,DO-15,TP	
....4	C598	2201-000991 C-CERAMIC,DISC:0.56NF,10%,2KV,Y5P,TP,7.5	
....4	DZ016	0403-001322 DIODE-ZENER:MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ016	0403-001322 DIODE-ZENER:MTZJ8.2B,7.78-8.19V,500mW,DO	
....4	DZ016	0403-000714 DIODE-ZENER:MTZJ3.3B,3.3V,3.32-3.53V,500	
....4	R834	2001-000109 R-CARBON(S):470OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R479	2001-000107 R-CARBON(S):150KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R451	2009-001109 R-TEMPERATURE:240ohm,5%,1/4W,AA,TP,2.3x6	
....4	PCB	AA41-00714C PCB-PWR DEF(DK):SP42W5HP,CEM-1,1L,C,1.6T	S.N.A
....4	RX801S	2002-001010 R-COMPOSITION:1.8Mohm,5%,1/2W,AA,TP,3.7x	
....4	C598	2201-000602 C-CERAMIC,DISC:0.56NF,5%,50V,SL,TP,10X3.	
....4	C701	2401-000852 C-AL:220uF,20%,35V,GP,TP,8x11.5mm,5	
....4	R458	2001-001194 R-CARBON(S):82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R125	2001-000539 R-CARBON:24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000878 R-CARBON:6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RZ123	2008-001155 R-FUSIBLE:3.9OHM,5%,1/2W,AF,TP,2.5X6.5MM	
....4	RZ124	2008-001155 R-FUSIBLE:3.9OHM,5%,1/2W,AF,TP,2.5X6.5MM	
....4	RZ125	2008-001155 R-FUSIBLE:3.9OHM,5%,1/2W,AF,TP,2.5X6.5MM	
....4	RZ126	2008-001155 R-FUSIBLE:3.9OHM,5%,1/2W,AF,TP,2.5X6.5MM	
....4	RZ127	2008-001155 R-FUSIBLE:3.9OHM,5%,1/2W,AF,TP,2.5X6.5MM	
....4	RZ128	2008-001155 R-FUSIBLE:3.9OHM,5%,1/2W,AF,TP,2.5X6.5MM	
....4	RZ142	2008-001155 R-FUSIBLE:3.9OHM,5%,1/2W,AF,TP,2.5X6.5MM	
....4	RZ143	2008-001155 R-FUSIBLE:3.9OHM,5%,1/2W,AF,TP,2.5X6.5MM	
....4	RZ144	2008-001155 R-FUSIBLE:3.9OHM,5%,1/2W,AF,TP,2.5X6.5MM	
....4	RZ145	2008-001155 R-FUSIBLE:3.9OHM,5%,1/2W,AF,TP,2.5X6.5MM	
....4	RZ146	2008-001155 R-FUSIBLE:3.9OHM,5%,1/2W,AF,TP,2.5X6.5MM	
....4	RZ147	2008-001155 R-FUSIBLE:3.9OHM,5%,1/2W,AF,TP,2.5X6.5MM	
....3		0202-000187 SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A
△	T401	AA26-50001S TRANS-HORIZ.DRIVE:-,6.0mH,-,44uH,-	
....3	L433	AA27-30003M COIL LINEARITY:-,5uH,OWA14x15,USRC0.1x60	
....3	IC851	1203-001400 IC-POWER PRESCALER:SE110N,TO-220(SIP),3P	
....3	C422	2303-000128 C-FILM,PPF:12nF,5%,1.6KV,BK,31x21x14,25m	
....3	C701	2401-003465 C-AL:680uF,20%,450V,GP,BK,35X60MM,22.5	
....3	T0076	BP39-00014A LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL1007	
....3	Q471	BP96-00083B ASSY HEAT SINK P-H/S,SCREW,KSC2335,OIL S	S.N.A
....3	CIS	0205-001027 OIL-SILICON:G746,-,-	S.N.A
....4	T0090	0502-001118 TR-POWER:KSC2335,NPN,40W,TO-220,ST,30-6	
....4	T0081	6003-000335 SCREW-TAPTITE:RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4	CIS	BP62-00009A HEAT SINK-PS:SP-42W5HP,A1050S,T2.0,25,49	S.N.A
....3	Q433	BP96-00083A ASSY HEAT SINK P-H/S,SCREW,KSD73,OIL SIL	S.N.A
....4	CIS	0205-001027 OIL-SILICON:G746,-,-	S.N.A
....4	T0090	0502-000298 TR-POWER:KSD73,NPN,30000mW,TO-220,TP,120	
....4	T0081	6003-000335 SCREW-TAPTITE:RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4	CIS	BP62-00009A HEAT SINK-PS:SP-42W5HP,A1050S,T2.0,25,49	S.N.A
....3	C701	2401-000787 C-AL:220uF,20%,160V,GP,TP,16x31.5mm	
△	VP801S	1405-000152 VARISTOR:560V,2500A,14x8.5mm,TP	
....3	GT301	AA60-40012D PIN-GT,ASSY:Ti,1.6-6.12.5,-,NYLON66	S.N.A
....3	C404	2306-000248 C-FILM,MPPF:680nF,5%,250V,BK,26.5x16.5mm	
△	T801S	BP26-00002A TRANS SWITCHING:EER5345,P55A,160V-280V,P	
....3	RS801	3601-000102 FUSE-AXIAL LEAD:125V,1A,FAST-ACTING,GLAS	
....3	C701	2401-003555 C-AL:3300uF,20%,25V,WT,TP,16x25.7.5	
....3	C701	2401-003555 C-AL:3300uF,20%,25V,WT,TP,16x25.7.5	

Loc. No.	Code No.	Description ; Specification	Remark
△	IC831S	AA96-00275M ASSY H/S;POWER,AA62-00051A,STR-X6459,FM	S.N.A
....4	CIS	0205-001027 OIL-SILICON:G746,-,-	S.N.A
....4	T0081	6003-000333 SCREW-TAPTITE:RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	CIS	AA62-00051A HEAT SINK-PS:-,SILVER,HOLE 31mm,ALL,	S.N.A
....4	IC063	BP13-00004A IC HYBRID:STR-X6459A,COMMANDO,7,-20 TO +	
....4	T0083	0402-001386 DIODE-RECTIFIER:FFP06F150S,1500V,6A,TO-	
....3	R833	2009-001096 R-METAL PLATE:0.07ohm,5%,5W,CL,BK,5x14x1	
....4	DZS801	0406-001007 DIODE-TVS:P6KE180A,171/180/189V,600W,CAS	
....3	R801	2003-000429 R-METAL OXIDE(S);1.5Kohm,5%,2W,AA,TP,4x1	
△	FP801S	3601-001007 FUSE-CARTRIDGE:250V,6.3A,TIME-LAG,GLASS,	
△	LX802S	AA29-00011A FILTER LINE NOISE:CZ32W8,-,0.20MAX,1.5KV	
△	LX803S	AA29-00011A FILTER LINE NOISE:CZ32W8,-,0.20MAX,1.5KV	
....3	L864	AA27-10002L COIL CHOKE:-,24uH,K,-,2A,-,24UH-K,10x10m	
....3	C701	2401-001675 C-AL:820uF,20%,200V,GP,BK,25x50mm,1	
....3	T0076	BP39-00005A LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL2547	
....3	T0076	BP39-00003A LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL1617	
....3	C419	2301-001343 C-FILM,MPPF:3.9NF,5%,2KV,BK,29X9.5X16MM,	
....3	C403	2301-001539 C-FILM,MPPF:1000NF,5%,400V,BK,28*25*18.2	
....3	C814	2301-001539 C-FILM,MPPF:1000NF,5%,400V,BK,28*25*18.2	
△	CX801S	2306-000318 C-FILM,MPPF:220NF,20%,250V,BK,-,22.5	
△	CX802S	2306-000318 C-FILM,MPPF:220NF,20%,250V,BK,-,22.5	
....3	L432	AA27-40003F COIL HORIZ. WIDTH:-,3.0MH,ER14x20,P10.35	
....3	C832	2301-001219 C-FILM,MPE-PF:3.9NF,5%,1.6KV,BK,29X8.5X	
....3	T0076	AA39-20009C LEAD CONNECTOR-ASSY:1P,40U,YFH800-01,16	
....3	C598	2201-000234 C-CERAMIC,DISC:0.15NF,5%,50V,COG,TP,9X3M	
....2	T0101	BP94-00134E ASSY PCB MISC-SENSOR ASSY:SENSOR	
....3		0202-000187 SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A
....3	CN906	3711-000447 CONNECTOR-HEADER:BOX,3P,1R,2.5MM,ANGLE,-	
....3		BP97-00208A ASSY SMD:HCM4215W3S/XAA	S.N.A
....4	Q01	0501-000342 TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
....4	PCB	AA41-00853A PCB-SERSON:SPV-42W5HRC,FR-4,2LA,1.6T,24	S.N.A
....4	D01	BP32-00001A SENSOR PHOTO:BCSS5030G1,-40 TO +85,0.42 U	
....4	R01	2007-000305 R-CHIP:10Mohm,5%,1/10W,TP,1608	
....4	R02	2007-000109 R-CHIP:1Mohm,5%,1/10W,TP,1608	
....4	R03	2007-000109 R-CHIP:1Mohm,5%,1/10W,TP,1608	
....4		0202-001167 SOLDER-CREAM:RX3603-2330HO,S45A,PASTE,SN	S.N.A
....2	T0100	BP94-00192A ASSY PCB MISC-A/V FRONT:SP42W5HPX/XEU,J5	
....3		0202-000187 SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A
....3	SW101	3404-000208 SWITCH-TACT:12V,50mA,120gf,6x6mm,SPST	
....3	CN906	3711-000447 CONNECTOR-HEADER:BOX,3P,1R,2.5MM,ANGLE,-	
....3	CN906	3711-003601 CONNECTOR-HEADER:BOX,12P,1R,2.5mm,ANGLE,	
....3	JK101	3722-000544 JACK-VHS:4P,11.5mm,AG,BLK,N	
....3	JK102	3722-001164 JACK-PIN:3P,3.4mm,SN,WH,YE:RE,#16-22	
....3		AA97-07426A ASSY AUTO-A/V FRONT:SP42W5HCX/XTT,J54A,C	S.N.A
....4	R125	2001-000006 R-CARBON:2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000273 R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000273 R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C689	2202-000121 C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
....4	C689	2202-000121 C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
....4	C689	2202-000121 C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
....4	C689	2202-000263 C-CERAMIC,MLC-AXIAL:470pF,10%,50V,Y5P,TP	
....4	C689	2202-000263 C-CERAMIC,MLC-AXIAL:470pF,10%,50V,Y5P,TP	
....4	F101	2901-000297 FILTER-EMI ON BOARD:-,3A,-,3.5x5,TP-	
....4	F101	2901-000297 FILTER-EMI ON BOARD:-,3A,-,3.5x5,TP-	
....4	0	AA41-00499D PCB-FRONT A/V:SPV-54T6SR,FR-1,1L,D,1.6T,	S.N.A
....3	T0105	BP96-00007B ASSY COVER P-SIDE,JACK:42W5,ABS HB G3676	
....4		AA64-02086L INLAY-AV:42W5,PS SHEET,T0.5,SILVER,J52A	S.N.A
....4		AA61-01128C HOLDER-SIDE AV:42W5,ABS HB,G3676,SV-704P	S.N.A
....4	T0150	AA64-02780C DOOR-AV:42W5,ABS HB,G3676,SV-704P	
....3	T0076	AA39-00260A LEAD CONNECTOR-ASSY:UL1007#26,UL/CSA,3P	
....3	T0076	BP39-00016A LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL2547	
....3	T0081	6003-001023 SCREW-TAPTITE:RW,H,+,B,M3,L10,ZPC(YEL),SW	S.N.A
....3		AA63-10002A BAND-TIE:NYLON66 V2,L100,NTR	S.N.A
....2	CIS	BP94-00220A ASSY PCB MISC-MASTER S/W:SVP-55W9HRTC,P5	
....3		0202-000187 SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A
....3	SWP01	3403-001130 SWITCH-PUSH:250VAC,5A,SPST,OFF-ON-OFF,-	
....3	T0081	6003-000334 SCREW-TAPTITE:RH,+,2S,M3,L6,ZPC(YEL),SWR	
....3		AA61-00719B HOLDER-MASTER:T6,W3,HIPS V0,BLK,J52A	S.N.A
....3		BP97-00134A ASSY AUTO-MASTER S/W:SVP-55W9HRTC,P55A	S.N.A
....4	PCB	AA41-00784A PCB-POWER S/W:SVP-55W9HRTC,CEM-1,1LA,1.	S.N.A
....4	EY02	6042-000002 EYELET:ID1.5,OD2,L2.8,Ni+SN,BSP3-1/2H	S.N.A
....4	EY01	6042-000002 EYELET:ID1.5,OD2,L2.8,Ni+SN,BSP3-1/2H	S.N.A
....4	GT01	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....4	GT02	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A
....3	CNW01	BP39-00048A LEAD CONNECTOR:PP5A/SVP-47W3HRT,UL1617#2	
....2	T0098	BP94-00579A ASSY PCB MISC-CONTROL:SP42W4HBX/XEU,J54A	
....3		0202-000187 SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
...3	LEDY01	0601-001381 LED:ROUND,RED/GRN,5.0MM,650/563NM					
...3	SWY08	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST					
...3	SWY07	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST					
...3	SWY06	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST					
...3	SWY05	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST					
...3	SWY01	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST					
...3	SWY03	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST					
...3	SWY04	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST					
...3	CN906	3711-000447 CONNECTOR-HEADER:BOX,3P,1R,2.5MM,ANGLE,-					
...3	CN906	3711-003353 CONNECTOR-HEADER:BOX,11P,1R,2.5mm,ANGLE,					
...3	T0081	6003-001023 SCREW-TAPTITE:RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A				
...3	RMV01	AA32-00012A MODULE REMOCON:ORC-50HF2,38KHZ,940NM,MES					
...3	T0076	AA39-00223A LEAD CONNECTOR-ASSY;,11P,800MM,67096-011					
...3	T0076	AA39-00259A LEAD CONNECTOR-ASSY;,UL1007#26,UL/CSA,3P					
...3		BP97-00201A ASSY AUTO:0	S.N.A				
...4	DZ016	0403-000510 DIODE-ZENER:MTZJ6.2B,6.2V,5.96-6.27V,500					
...4	DZ016	0403-000510 DIODE-ZENER:MTZJ6.2B,6.2V,5.96-6.27V,500					
...4	DZ016	0403-000510 DIODE-ZENER:MTZJ6.2B,6.2V,5.96-6.27V,500					
...4	QY02	0504-000123 TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,T					
...4	QY01	0504-000123 TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,T					
...4	RY07	2001-000020 R-CARBON(S):220HM,5%,1/2W,AA,TP,2.4X6.4MM					
...4	RY09	2001-000109 R-CARBON(S):4700HM,5%,1/2W,AA,TP,2.4X6.4					
...4	RY01	2001-000109 R-CARBON(S):4700HM,5%,1/2W,AA,TP,2.4X6.4					
...4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
...4	R125	2001-000832 R-CARBON:5100HM,5%,1/8W,AA,TP,1.8X3.2MM					
...4	R125	2001-000832 R-CARBON:5100HM,5%,1/8W,AA,TP,1.8X3.2MM					
...4	R125	2001-000832 R-CARBON:5100HM,5%,1/8W,AA,TP,1.8X3.2MM					
...4	R125	2001-000924 R-CARBON:6800HM,5%,1/8W,AA,TP,1.8X3.2MM					
...4	RY08	2001-001108 R-CARBON(S):22KOHM,5%,1/2W,AA,TP,2.4X6.4					
...4	C701	2401-002009 C-AL:100uF,20%,16V,GP,TP,6.3x7.5					
...4	0	AA41-00768C PCB CONTROL:ST43T8,1L,1.6T,245x245,J54A,	S.N.A				

## ASSY P/MATERIAL

1	BP92-00009A	ASSY P/MATERIAL:42W5,SVP-42W5HR	S.N.A
..2	AA60-40006A	PIN-STAPLE:AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A
..2	AA63-10007C	BAND-PP:W18,CLEA,1G	S.N.A
..2	6902-000061	BAG AIR:LDPE,TO.2,L1000,W500,TRP,,	S.N.A
..2	6902-000008	BAG PE:HDPE/NITRON/HDPE,TO.015/TO.5/TO.0	S.N.A

## ASSY ACCESSORY

1	M0016	BP92-00073A	ASSY ACCESSORY:SP42W5HPX/XEU,J54A	S.N.A
..2	T0116	AA39-00006A	CABLE RCA:,3000MM	
..2		AA68-20051A	MANUAL-S/NETWORK:ALL,W/P 100(G),B5,ENG,S	S.N.A
..2	T0074	BP59-00008A	REMOCON:,TM65A,COMMOANDO,J54A,49,L/GRAY,	
...3	T0122	2802-000194	RESONATOR-CERAMIC:8MHz,1.0%,TP,8.5x4.5x5	
...3	T0119	AA09-00371A	IC MICOM:SZTM-839C R-52MX,28PIN,16KBYTE,	
..2	CIS	BP68-00023A	MANUAL USERS:SP42W5HP,ENG,W/P100G,J54A,B	
..2	1	6801-001014	CARD-REGISTRATION:XEU,ENG,MOJO100,L150,W	S.N.A
..2		6902-000018	BAG PE:LDPE,TO.1,W280,L400,GRY,8,2-	S.N.A
1		BP92-00499A	ASSY BOX:SP42W4HPS/XEF,P55A	S.N.A
1		BP92-00639P	ASSY LABEL:SP42W4HBX/XEU,J54A	

# MEMO